


Network Calculus Tests – Feed Forward Network Settings

Version 2.0 beta (2015-Jul-02)



© Steffen Bondorf 2013 - 2015, Some Rights Reserved.

Except where otherwise noted, this work is licensed under Creative Commons Attribution-ShareAlike 4.0.
See <http://creativecommons.org/licenses/by-sa/4.0/>

General Information

- The network calculus analyses presented in this document were created for the purpose of testing the Disco Deterministic Network Calculator (DiscoDNC)¹ – an open-source deterministic network calculus tool developed by the *Distributed Computer Systems (DISCO) Lab* at the University of Kaiserslautern.
- Naming of the individual network settings depicts the name of the according functional test for the DiscoDNC.
- The naming scheme used in this document is detailed in `NetworkCalculus_NamingScheme.pdf`.
- Arrival bounds for `PmooArrivalBound.java` and analyses using them are listed only if results differ from `PbooArrivalBound_Concatenation.java`.

Changelog:

Version 1.1 (2014-Dec-30):


- Streamlined the PMOO left-over latency $T_{e2e}^{l.o.f}$ computation.
- Adaption to naming scheme version 1.1.

Version 2.0 beta (2015-Jul-02):

- Rework of Arrival Bounds documentation
 - Parameters: see DiscoDNC's `computeArrivalBounds(Server server, Set<Flow> flows_to_bound, Flow flow_of_interest)`.
 - Bounding arrivals moved to the analysis requiring the specific bounds if they differ between flows of interest (may cause duplication).
 - The algebraic derivations is included within the tabular bounding procedure. They are adapted to `PbooArrivalBound`, yet, in contrast to the current DiscoDNC code, they may reuse known results.
- The naming scheme was slightly updated to include sets of servers \mathbb{S} and sets of Flows \mathbb{F} .
- Minor consistency fixes for variable names.

¹<http://disco.cs.uni-kl.de/index.php/projects/disco-dnc>

FeedForward_1SC_3Flows_1AC_3Paths



$\mathbb{S} = \{s_0, s_1, s_2, s_3\}$ with

$$\beta_{s_0} = \beta_{s_1} = \beta_{s_2} = \beta_{s_3} = \beta_{R_{s_i}, T_{s_i}} = \beta_{20,20}, \quad i \in \{0, 1, 2\}$$

$\mathbb{F} = \{f_0, f_1, f_2\}$ with

$$\alpha^{f_0} = \alpha^{f_1} = \alpha^{f_2} = \gamma_{r^{f_n}, b^{f_n}} = \gamma_{5,25}, \quad n \in \{0, 1, 2\}$$

Flow f_0

Total Flow Analysis

Arrival Bounds

$(s_1, \{f_0\}, \emptyset) =: \alpha_{s_1}^{f_0}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \oslash \beta_{s_0}^{\text{l.o.}, f_0}$		
$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{0,0}$	
$\beta_{s_0}^{\text{l.o.}, f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$ $= \beta_{R_{s_0}^{\text{l.o.}, f_0}, T_{s_0}^{\text{l.o.}, f_0}}$	$= \beta_{s_0} = \beta_{20,20}$	
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \oslash \beta_{s_0}^{\text{l.o.}, f_0}$ $= \gamma_{r_{s_1}^{f_0}, b_{s_1}^{f_0}}$	$r_{s_1}^{f_0}$	$= 5$
	$b_{s_1}^{f_0}$	$= \alpha^{f_0}(T^{\text{l.o.}})$
		$= 5 \cdot 20 + 25$
		$= 125$
	$=$	$= \gamma_{5,125}$

$(s_3, \{f_1\}, \emptyset) =: \alpha_{s_3}^{f_1}$ $(s_1, \{f_2\}, \emptyset) =: \alpha_{s_1}^{f_2}$ $=: \alpha_{s_i}^{f_n}$ with $(n, i) \in \{(1, 3), (2, 1)\}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \oslash \beta_{s_2}^{\text{l.o.}, f_n}$		
$\alpha_{s_2}^{x(f_n)}$	$= \gamma_{5,25}$	
$\beta_{s_2}^{\text{l.o.}, f_n} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_n)}$ $= \beta_{R_{s_2}^{\text{l.o.}, f_n}, T_{s_2}^{\text{l.o.}, f_n}}$	$R_{s_2}^{\text{l.o.}, f_n}$	$\left[R_{s_2} - r_{s_2}^{x(f_n)}\right]^+ = 20 - 5$ $= 15$
	$T_{s_2}^{\text{l.o.}, f_n}$	$\beta_{s_2} = b_{s_2}^{x(f_n)} \quad \beta_{s_2} = \alpha_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 25 \quad 20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 21\frac{1}{4} \quad t = 28\frac{1}{3}$
	$=$	$= \beta_{15, 28\frac{1}{3}}$
	$=$	$= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \oslash \beta_{s_2}^{\text{l.o.}, f_n}$ $= \gamma_{r_{s_i}^{f_n}, b_{s_i}^{f_n}}$	$r_{s_i}^{f_n}$	$= 5$
	$b_{s_i}^{f_n}$	$= \alpha^{f_n}(T_{s_2}^{\text{l.o.}, f_n})$
		$= 5 \cdot 21\frac{1}{4} + 25$
		$= 131\frac{1}{4}$
	$=$	$= \gamma_{5, 131\frac{1}{4}}$

$(s_3, \{f_0\}, \emptyset) =: \alpha_{s_3}^{f_0}$		FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_3}^{f_0} =$ $\alpha^{f_0} \oslash (\beta_{s_0}^{1.o.f_0} \otimes \beta_{s_1}^{1.o.f_0})$ (reuse of previous result) $=$ $\alpha^{f_0} \oslash \beta_{s_0}^{1.o.f_0} \oslash \beta_{s_1}^{1.o.f_0}$ $=$ $\alpha_{s_1}^{f_0} \oslash \beta_{s_1}^{1.o.f_0}$			
		$= \alpha_{s_1}^{f_2} = \gamma_{5,131\frac{1}{4}}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,166\frac{2}{3}}$
		$\left[R_{s_1} - r_{s_1}^{x(f_0)} \right]^+ = 20 - 5$ $= 15$	
		$\beta_{s_1} = b_{s_1}^{x(f_0)}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$
$\beta_{s_1}^{1.o.f_0} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{1.o.f_0}, T_{s_1}^{1.o.f_0}}$	$R_{s_1}^{1.o.f_0}$	$20 \cdot [t - 20]^+ = 131\frac{1}{4}$	$20 \cdot [t - 20]^+ = 5 \cdot t + 166\frac{2}{3}$
	$T_{s_1}^{1.o.f_0}$	$t = 26\frac{9}{16}$	$t = 37\frac{7}{8}$
	$=$	$= \beta_{15,26\frac{9}{16}}$	$= \beta_{15,37\frac{7}{8}}$
$\alpha_{s_1}^{f_0}$		$= \gamma_{5,125}$	
$\alpha_{s_3}^{f_0} = \alpha^{f_0} \oslash \beta_{s_1}^{1.o.f_0}$ $= \gamma_{r_{s_3}^{f_0}, b_{s_3}^{f_0}}$	$r_{s_3}^{f_0}$	$= 5$	
	$b_{s_3}^{f_0}$	$= \alpha_{s_1}^{f_0} (T_{s_1}^{1.o.f_0})$	$= \alpha_{s_1}^{f_0} (T_{s_1}^{1.o.f_0})$
		$= 5 \cdot 26\frac{9}{16} + 125$	$= 5 \cdot 37\frac{7}{8} + 125$
		$= 257\frac{13}{16}$	$= 313\frac{8}{9}$
$=$		$= \gamma_{5,257\frac{13}{16}}$	$= \gamma_{5,313\frac{8}{9}}$

Analysis

TFA		FIFO Multiplexing	Arbitrary Multiplexing
s_0	α_{s_0}	$= \alpha_{s_0}^{f_0} = \gamma_{5,25}$	
	$D_{s_0}^{f_0}$	$\beta_{s_0} = b_{s_0}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$	FIFO per micro flow $\beta_{s_0} = b_{s_0}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$
	$B_{s_0}^{f_0}$	$\alpha_{s_0}(T_{s_0}) = 20 \cdot 5 + 25$ $= 125$	
s_1	α_{s_1}	$= \alpha_{s_1}^{f_0} + \alpha_{s_1}^{f_2}$ $= \gamma_{5,125} + \gamma_{5,131\frac{1}{4}}$ $= \gamma_{10,256\frac{1}{4}}$	$= \alpha_{s_1}^{f_0} + \alpha_{s_1}^{f_2}$ $= \gamma_{5,125} + \gamma_{5,166\frac{2}{3}}$ $= \gamma_{10,291\frac{2}{3}}$
	$D_{s_1}^{f_0}$	$\beta_{s_1} = b_{s_1}$ $20 \cdot [t - 20]^+ = 256\frac{1}{4}$ $t = 32\frac{13}{16}$	$\beta_{s_1} = \alpha_{s_1}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 291\frac{2}{3}$ $t = 69\frac{1}{6}$
	$B_{s_1}^{f_0}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 256\frac{1}{4}$ $= 456\frac{1}{4}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 291\frac{2}{3}$ $= 491\frac{2}{3}$
s_3	α_{s_3}	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$ $= \gamma_{5,257\frac{13}{16}} + \gamma_{5,131\frac{1}{4}}$ $= \gamma_{10,389\frac{1}{16}}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$ $= \gamma_{5,313\frac{8}{9}} + \gamma_{5,166\frac{2}{3}}$ $= \gamma_{10,480\frac{5}{9}}$
	$D_{s_3}^{f_0}$	$\beta_{s_3} = b_{s_3}$ $20 \cdot [t - 20]^+ = 389\frac{1}{16}$ $t = 39\frac{29}{64}$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 480\frac{5}{9}$ $t = 88\frac{5}{90}$
	$B_{s_3}^{f_0}$	$\alpha_{s_3}(T_{s_3}) = 10 \cdot 20 + 389\frac{1}{16}$ $= 589\frac{1}{16}$	$\alpha_{s_3}(T_{s_3}) = 10 \cdot 20 + 480\frac{5}{9}$ $= 680\frac{5}{9}$
D^{f_0}		$= \sum_{i=\{0,1,3\}} D_{s_i}^{f_0}$ $= 93\frac{33}{64}$	$= \sum_{i=\{0,1,3\}} D_{s_i}^{f_0}$ $= 178\frac{17}{36}$
B^{f_0}		$= \max_{i=\{0,1,3\}} B_{s_i}^{f_0}$ $= 589\frac{1}{16}$	$= \max_{i=\{0,1,3\}} B_{s_i}^{f_0}$ $= 680\frac{5}{9}$

Separate Flow Analysis and PMOO Analysis

Arrival Bounds

$(s_3, \{f_1\}, f_0) =: \alpha_{s_3}^{f_1}$ $(s_1, \{f_2\}, f_0) =: \alpha_{s_1}^{f_2}$ $=: \alpha_{s_i}^{f_n}$ with $(n, i) \in \{(1, 3), (2, 1)\}$		FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \oslash \beta_{s_2}^{l.o.f_n}$			
$\alpha_{s_2}^{x(f_n)}$		$= \gamma_{5,25}$	
$\beta_{s_2}^{l.o.f_n} = \beta_{s_2} \oslash \alpha_{s_2}^{x(f_n)}$ $= \beta_{R_{s_2}^{l.o.f_n}, T_{s_2}^{l.o.f_n}}$	$R_{s_2}^{l.o.f_n}$	$\left[R_{s_2} - r_{s_2}^{x(f_n)} \right]^+ = 20 - 5$ $= 15$	
	$T_{s_2}^{l.o.f_n}$	$\beta_{s_2} = b_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$	$\beta_{s_2} = \alpha_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \oslash \beta_{s_2}^{l.o.f_n}$ $= \gamma_{r_{s_i}^{f_n}, b_{s_i}^{f_n}}$	$r_{s_i}^{f_n}$	$= 5$	
	$b_{s_i}^{f_n}$	$= \alpha^{f_n} (T_{s_2}^{l.o.f_n})$ $= 5 \cdot 21\frac{1}{4} + 25$ $= 131\frac{1}{4}$	$= \alpha^{f_n} (T_{s_2}^{l.o.f_n})$ $= 5 \cdot 28\frac{1}{3} + 25$ $= 166\frac{2}{3}$
	$=$	$= \gamma_{5, 131\frac{1}{4}}$	$= \gamma_{5, 166\frac{2}{3}}$
	$=$	$= \gamma_{5, 131\frac{1}{4}}$	$= \gamma_{5, 166\frac{2}{3}}$

Remark:

In this network setting, we have $(s_3, \{f_1\}, f_0) = (s_3, \{f_1\}, \emptyset)$ and $(s_1, \{f_2\}, f_0) = (s_1, \{f_2\}, \emptyset)$ because neither (cross-)flow f_1 nor f_2 interferes with the flow of interest f_0 on multiple consecutive hops.

Analyses

SFA			FIFO Multiplexing	Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$		$= \gamma_{0,0}$	
	$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$		$= \beta_{20,20}$	
s_1	$\alpha_{s_1}^{x(f_0)}$		$= \alpha_{s_1}^{f_2} = \gamma_{5,131\frac{1}{4}}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,166\frac{2}{3}}$
	$\beta_{s_1}^{l.o.f_0} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{l.o.f_0}, T_{s_1}^{l.o.f_0}}$	$R_{s_1}^{l.o.f_0}$	$\left[R_{s_1} - r_{s_1}^{x(f_0)} \right]^+ = 20 - 5$ $= 15$	
		$T_{s_1}^{l.o.f_0}$	$\beta_{s_1} = b_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 131\frac{1}{4}$ $t = 26\frac{9}{16}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 166\frac{2}{3}$ $t = 37\frac{7}{9}$
		$=$	$= \beta_{15,26\frac{9}{16}}$	$= \beta_{15,37\frac{7}{9}}$
s_3	$\alpha_{s_3}^{x(f_0)}$		$= \alpha_{s_3}^{f_1} = \gamma_{5,131\frac{1}{4}}$	$= \alpha_{s_3}^{f_1} = \gamma_{5,166\frac{2}{3}}$
	$\beta_{s_3}^{l.o.f_0} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_0)}$ $= \beta_{R_{s_3}^{l.o.f_0}, T_{s_3}^{l.o.f_0}}$	$R_{s_3}^{l.o.f_0}$	$\left[R_{s_3} - r_{s_3}^{x(f_0)} \right]^+ = 20 - 5$ $= 15$	
		$T_{s_3}^{l.o.f_0}$	$\beta_{s_3} = b_{s_3}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 131\frac{1}{4}$ $t = 26\frac{9}{16}$	$\beta_{s_3} = \alpha_{s_3}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 166\frac{2}{3}$ $t = 37\frac{7}{9}$
		$=$	$= \beta_{15,26\frac{9}{16}}$	$= \beta_{15,37\frac{7}{9}}$
$\beta_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} = \beta_{R_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0}, T_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0}}$			$= \bigotimes_{i=\{0,1,3\}} \beta_{s_i}^{l.o.f_0}$ $= \beta_{15,73\frac{1}{8}}$	$= \bigotimes_{i=\{0,1,3\}} \beta_{s_i}^{l.o.f_0}$ $= \beta_{15,95\frac{5}{9}}$
D^{f_0}			$\beta_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} = b^{f_0}$ $15 \cdot \left[t - 73\frac{1}{8} \right]^+ = 25$ $t = 74\frac{19}{24}$	$\beta_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} = b^{f_0}$ $15 \cdot \left[t - 95\frac{5}{9} \right]^+ = 25$ $t = 97\frac{2}{9}$
B^{f_0}			$\alpha^{f_0} \left(T_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} \right) = 5 \cdot 73\frac{1}{8} + 25$ $= 390\frac{5}{8}$	$\alpha^{f_0} \left(T_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} \right) = 5 \cdot 95\frac{5}{9} + 25$ $= 502\frac{7}{9}$

PMOO		Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{0,0}$
	$\alpha_{s_0}^{\bar{x}(f_0)}$	
s_1	$\alpha_{s_1}^{x(f_0)}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,166\frac{2}{3}}$
	$\alpha_{s_1}^{\bar{x}(f_0)}$	
s_3	$\alpha_{s_3}^{x(f_0)}$	$= \alpha_{s_3}^{f_1} = \gamma_{5,166\frac{2}{3}}$
	$\alpha_{s_3}^{\bar{x}(f_0)}$	
$\beta_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} = \beta_{R_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0}, T_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0}}$	$R_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0}$	$= \bigwedge_{i \in \{0,1,3\}} \left(R_{s_i} - r_{s_i}^{x(f_0)} \right)$ $= (20 - 5) \wedge (20 - 5) \wedge (20 - 5)$ $= 15$
	$T_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0}$	$= \sum_{i \in \{0,1,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_0)} + r_{s_i}^{x(f_0)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_0}} \right)$ $= 20 + \frac{0 + 0 \cdot 20}{15} + 20 + \frac{166\frac{2}{3} + 5 \cdot 20}{15} + 20 + \frac{166\frac{2}{3} + 5 \cdot 20}{15}$ $= 60 + \frac{533\frac{1}{3}}{15}$ $= 95\frac{5}{9}$
	$=$	$= \beta_{15, 95\frac{5}{9}}$
D^{f_0}		$\beta_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} = b^{f_0}$ $15 \cdot \left[t - 95\frac{5}{9} \right]^+ = 25$ $t = 97\frac{2}{9}$
B^{f_0}		$\alpha^{f_0} \left(T_{\langle s_0, s_1, s_3 \rangle}^{l.o.f_0} \right) = 5 \cdot 95\frac{5}{9} + 25$ $= 502\frac{7}{9}$

Flow f_1

Total Flow Analysis

Arrival Bounds

$(s_3, \{f_1\}, \emptyset) =: \alpha_{s_3}^{f_1}$ $(s_1, \{f_2\}, \emptyset) =: \alpha_{s_1}^{f_2}$ $=: \alpha_{s_i}^{f_n}$ with $(n, i) \in \{(1, 3), (2, 1)\}$		FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \oslash \beta_{s_2}^{l.o.f_n}$			
$\alpha_{s_2}^{x(f_n)}$		$= \gamma_{5,25}$	
$\beta_{s_2}^{l.o.f_n} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_n)}$ $= \beta_{R_{s_2}^{l.o.f_n}, T_{s_2}^{l.o.f_n}}$	$R_{s_2}^{l.o.f_n}$	$\left[R_{s_2} - r_{s_2}^{x(f_n)}\right]^+ = 20 - 5$ $= 15$	
	$T_{s_2}^{l.o.f_n}$	$\beta_{s_2} = b_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$	$\beta_{s_2} = \alpha_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \oslash \beta_{s_2}^{l.o.f_n}$ $= \gamma_{r_{s_i}^{f_n}, b_{s_i}^{f_n}}$	$r_{s_i}^{f_n}$	$= 5$	
	$b_{s_i}^{f_n}$	$= \alpha^{f_n} (T_{s_2}^{l.o.f_n})$ $= 5 \cdot 21\frac{1}{4} + 25$ $= 131\frac{1}{4}$	$= \alpha^{f_n} (T_{s_2}^{l.o.f_n})$ $= 5 \cdot 28\frac{1}{3} + 25$ $= 166\frac{2}{3}$
	$=$	$= \gamma_{5, 131\frac{1}{4}}$	$= \gamma_{5, 166\frac{2}{3}}$
	$=$	$= \gamma_{5, 131\frac{1}{4}}$	$= \gamma_{5, 166\frac{2}{3}}$

$(s_3, \{f_0\}, \emptyset) =: \alpha_{s_3}^{f_0}$		FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_3}^{f_0} = \alpha^{f_0} \oslash (\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0})$			
$\alpha_{s_0}^{x(f_0)}$		$= \gamma_{0,0}$	
$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$ $= \beta_{R_{s_0}^{l.o.f_0}, T_{s_0}^{l.o.f_0}}$		$= \beta_{s_0} = \beta_{20,20}$	
$\alpha_{s_1}^{x(f_0)}$		$= \alpha_{s_1}^{f_2} = \gamma_{5, 131\frac{1}{4}}$	$= \alpha_{s_1}^{f_2} = \gamma_{5, 166\frac{2}{3}}$
$\beta_{s_1}^{l.o.f_0} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{l.o.f_0}, T_{s_1}^{l.o.f_0}}$	$R_{s_1}^{l.o.f_0}$	$\left[R_{s_1} - r_{s_1}^{x(f_0)}\right]^+ = 20 - 5$ $= 15$	
	$T_{s_1}^{l.o.f_0}$	$\beta_{s_1} = b_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 131\frac{1}{4}$ $t = 26\frac{9}{16}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 166\frac{2}{3}$ $t = 37\frac{7}{8}$
	$=$	$= \beta_{15, 26\frac{9}{16}}$	$= \beta_{15, 37\frac{7}{8}}$
	$=$	$= \beta_{15, 26\frac{9}{16}}$	$= \beta_{15, 37\frac{7}{8}}$
$\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0} = \beta_{\langle s_0, s_1 \rangle}^{l.o.f_0}$		$= \beta_{20,20} \otimes \beta_{15, 26\frac{9}{16}}$ $= \beta_{15, 46\frac{9}{16}}$	$= \beta_{20,20} \otimes \beta_{15, 37\frac{7}{8}}$ $= \beta_{15, 57\frac{7}{8}}$
$\alpha_{s_3}^{f_0} = \alpha^{f_0} \oslash (\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0})$	$r_{s_3}^{f_0}$	$= 5$	
	$b_{s_3}^{f_0}$	$= \alpha_{s_1}^{f_0} (T_{\langle s_0, s_1 \rangle}^{l.o.f_0})$ $= 5 \cdot 46\frac{9}{16} + 25$ $= 257\frac{13}{16}$	$= \alpha_{s_1}^{f_0} (T_{\langle s_0, s_1 \rangle}^{l.o.f_0})$ $= 5 \cdot 57\frac{7}{8} + 25$ $= 313\frac{8}{9}$
	$=$	$= \gamma_{5, 257\frac{13}{16}}$	$= \gamma_{5, 313\frac{8}{9}}$
	$=$	$= \gamma_{5, 257\frac{13}{16}}$	$= \gamma_{5, 313\frac{8}{9}}$

Remark:

PmooArrivalBound.java will have the same result as PbooArrivalBound_Concatenation.java because f_0 does not have cross-traffic interfering on multiple consecutive hops.

Analysis

TFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	α_{s_2}	$= \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_2}$ $= \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{10,50}$	
	$D_{s_2}^{f_1}$	$\beta_{s_2} = b_{s_2}$ $20 \cdot [t - 20]^+ = 50$ $t = 22\frac{1}{2}$	$\beta_{s_2} = \alpha_{s_2}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 50$ $t = 45$
	$B_{s_2}^{f_1}$	$\alpha_{s_2}(T_{s_2}) = 20 \cdot 10 + 50$ $= 250$	
s_3	α_{s_3}	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$ $= \gamma_{5,257\frac{13}{16}} + \gamma_{5,131\frac{1}{4}}$ $= \gamma_{10,389\frac{1}{16}}$	
	$D_{s_3}^{f_1}$	$\beta_{s_3} = b_{s_3}$ $20 \cdot [t - 20]^+ = 389\frac{1}{16}$ $t = 39\frac{29}{64}$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 480\frac{5}{9}$ $t = 88\frac{5}{90}$
	$B_{s_3}^{f_1}$	$\alpha_{s_3}(T_{s_3}) = 10 \cdot 20 + 389\frac{1}{16}$ $= 589\frac{1}{16}$	
D^{f_1}		$= \sum_{i=2}^3 D_{s_i}^{f_1}$ $= 61\frac{61}{64}$	$= \sum_{i=2}^3 D_{s_i}^{f_1}$ $= 185\frac{5}{9}$
B^{f_1}		$= \max_{i=\{2,3\}} B_{s_i}^{f_1}$ $= 589\frac{1}{16}$	$= \max_{i=\{2,3\}} B_{s_i}^{f_1}$ $= 680\frac{5}{9}$

Separate Flow Analysis and PMOO Analysis

Arrival Bounds

$(s_1, \{f_2\}, \emptyset) =: \alpha_{s_1}^{f_2}$		FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_1}^{f_2} = \alpha^{f_2} \oslash \beta_{s_2}^{l.o.f_2}$			
$\alpha_{s_2}^{x(f_2)}$		$= \gamma_{5,25}$	
$\beta_{s_2}^{l.o.f_2} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_2)}$ $= \beta_{R_{s_2}^{l.o.f_2}, T_{s_2}^{l.o.f_2}}$	$R_{s_2}^{l.o.f_n}$	$\left[R_{s_2} - r_{s_2}^{x(f_2)} \right]^+ = 20 - 5$ $= 15$	
	$T_{s_2}^{l.o.f_n}$	$\beta_{s_2} = b_{s_2}^{x(f_2)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$	$\beta_{s_2} = \alpha_{s_2}^{x(f_2)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$
	$=$	$= \beta_{15,21\frac{1}{4}}$	$= \beta_{15,28\frac{1}{3}}$
	$=$	$= \beta_{15,21\frac{1}{4}}$	$= \beta_{15,28\frac{1}{3}}$
$\alpha_{s_1}^{f_2} = \alpha^{f_2} \oslash \beta_{s_2}^{l.o.f_2}$		$= 5$	
$= \gamma_{r_{s_1}^{f_2}, b_{s_1}^{f_2}}$		$= \alpha^{f_2} (T_{s_2}^{l.o.f_2})$	
		$= 5 \cdot 21\frac{1}{4} + 25$	
		$= 131\frac{1}{4}$	
$=$		$= \gamma_{5,131\frac{1}{4}}$	$= \gamma_{5,166\frac{2}{3}}$

$(s_3, \{f_0\}, \emptyset) =: \alpha_{s_3}^{f_0}$		FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_3}^{f_0} = \alpha^{f_0} \oslash (\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0})$			
$\alpha_{s_0}^{x(f_0)}$		$= \gamma_{0,0}$	
$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$ $= \beta_{R_{s_0}^{l.o.f_0}, T_{s_0}^{l.o.f_0}}$		$= \beta_{s_0} = \beta_{20,20}$	
$\alpha_{s_1}^{x(f_0)}$		$= \alpha_{s_1}^{f_2} = \gamma_{5,131\frac{1}{4}}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,166\frac{2}{3}}$
$\beta_{s_1}^{l.o.f_0} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{l.o.f_0}, T_{s_1}^{l.o.f_0}}$	$R_{s_1}^{l.o.f_0}$	$\left[R_{s_1} - r_{s_1}^{x(f_0)} \right]^+ = 20 - 5$ $= 15$	
	$T_{s_1}^{l.o.f_0}$	$\beta_{s_1} = b_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 131\frac{1}{4}$ $t = 26\frac{9}{16}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 166\frac{2}{3}$ $t = 37\frac{7}{8}$
	$=$	$= \beta_{15,26\frac{9}{16}}$	$= \beta_{15,37\frac{7}{8}}$
	$=$	$= \beta_{15,26\frac{9}{16}}$	$= \beta_{15,37\frac{7}{8}}$
$\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0} = \beta_{\langle s_0, s_1 \rangle}^{l.o.f_0}$		$= \beta_{20,20} \otimes \beta_{15,26\frac{9}{16}}$	$= \beta_{20,20} \otimes \beta_{15,37\frac{7}{8}}$
		$= \beta_{15,46\frac{9}{16}}$	$= \beta_{15,57\frac{7}{8}}$
$\alpha_{s_3}^{f_0} = \alpha^{f_0} \oslash (\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0})$		$= 5$	
		$= \alpha_{s_1}^{f_0} (T_{\langle s_0, s_1 \rangle}^{l.o.f_0})$	$= \alpha_{s_1}^{f_0} (T_{\langle s_0, s_1 \rangle}^{l.o.f_0})$
		$= 5 \cdot 46\frac{9}{16} + 25$	$= 5 \cdot 57\frac{7}{8} + 25$
		$= 257\frac{13}{16}$	$= 313\frac{8}{9}$
$=$		$= \gamma_{5,257\frac{13}{16}}$	$= \gamma_{5,313\frac{8}{9}}$

Remark:

PmooArrivalBound.java will have the same result as PbooArrivalBound_Concatenation.java because f_0 does not have cross-traffic interfering on multiple consecutive hops.

Analyses

SFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_1)}$	$= \alpha^{f_2} = \gamma_{5,25}$	
	$\beta_{s_2}^{l.o.f_1} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_1)}$ $= \beta_{R_{s_2}^{l.o.f_1}, T_{s_2}^{l.o.f_1}}$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
s_3	$\alpha_{s_3}^{x(f_1)} = \alpha_{s_3}^{f_0}$	$= \gamma_{5, 257\frac{13}{16}}$	$= \gamma_{5, 313\frac{8}{9}}$
	$\beta_{s_3}^{l.o.f_1} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_1)}$ $= \beta_{R_{s_3}^{l.o.f_1}, T_{s_3}^{l.o.f_1}}$	$[R_{s_3} - r_{s_3}^{x(f_1)}]^+ = 20 - 5$ $= 15$	
		$\beta_{s_3} = b_{s_3}^{x(f_1)}$ $20 \cdot [t - 20]^+ = 257\frac{13}{16}$ $t = 32\frac{57}{64}$	$\beta_{s_3} = \alpha_{s_3}^{x(f_1)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 313\frac{8}{9}$ $t = 47\frac{16}{27}$
		$= \beta_{15, 32\frac{57}{64}}$	$= \beta_{15, 47\frac{16}{27}}$
	$\beta_{\langle s_2, s_3 \rangle}^{l.o.f_1} = \beta_{R_{\langle s_2, s_3 \rangle}^{l.o.f_1}, T_{\langle s_2, s_3 \rangle}^{l.o.f_1}}$	$= \bigotimes_{i=2}^3 \beta_{s_i}^{l.o.f_1}$ $= \beta_{15, 54\frac{9}{64}}$	$= \bigotimes_{i=2}^3 \beta_{s_i}^{l.o.f_1}$ $= \beta_{15, 75\frac{25}{27}}$
	D^{f_1}	$\beta_{\langle s_2, s_3 \rangle}^{l.o.f_1} = b^{f_1}$ $15 \cdot \left[t - 54\frac{9}{64}\right]^+ = 25$ $t = 55\frac{155}{192}$	$\beta_{\langle s_2, s_3 \rangle}^{l.o.f_1} = b^{f_1}$ $15 \cdot \left[t - 75\frac{25}{27}\right]^+ = 25$ $t = 77\frac{16}{27}$
	B^{f_1}	$\alpha^{f_1} \left(T_{\langle s_2, s_3 \rangle}^{l.o.f_1}\right) = 5 \cdot 54\frac{9}{64} + 25$ $= 295\frac{45}{64}$	$\alpha^{f_1} \left(T_{\langle s_2, s_3 \rangle}^{l.o.f_1}\right) = 5 \cdot 75\frac{25}{27} + 25$ $= 404\frac{17}{27}$

PMOO		Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_1)}$	$= \alpha_{s_2}^{f_2} = \gamma_{5,25}$
	$\alpha_{s_2}^{\bar{x}(f_1)}$	
s_3	$\alpha_{s_3}^{x(f_1)}$	$= \alpha_{s_3}^{f_0} = \gamma_{5, 313\frac{8}{9}}$
	$\alpha_{s_3}^{\bar{x}(f_1)}$	
$\beta_{\langle s_2, s_3 \rangle}^{l.o.f_1} = \beta_{R_{\langle s_2, s_3 \rangle}^{l.o.f_1}, T_{\langle s_2, s_3 \rangle}^{l.o.f_1}}$	$R_{\langle s_2, s_3 \rangle}^{l.o.f_1}$	$= \bigwedge_{i \in \{2,3\}} \left(R_{s_i} - r_{s_i}^{x(f_1)}\right)$ $= (20 - 5) \wedge (20 - 5)$ $= 15$
	$T_{\langle s_2, s_3 \rangle}^{l.o.f_1}$	$= \sum_{i \in \{2,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_1)} + r_{s_i}^{x(f_1)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_1}}\right)$ $= 20 + \frac{25 + 5 \cdot 20}{15} + 20 + \frac{313\frac{8}{9} + 5 \cdot 20}{15}$ $= 40 + \frac{538\frac{8}{9}}{15}$ $= 75\frac{25}{27}$
		$= \beta_{15, 75\frac{25}{27}}$
	$=$	
	D^{f_1}	$\beta_{\langle s_2, s_3 \rangle}^{l.o.f_1} = b^{f_1}$ $15 \cdot \left[t - 75\frac{25}{27}\right]^+ = 25$ $t = 77\frac{16}{27}$
	B^{f_1}	$\alpha^{f_1} \left(T_{\langle s_2, s_3 \rangle}^{l.o.f_1}\right) = 5 \cdot 75\frac{25}{27} + 25$ $= 404\frac{17}{27}$

Flow f_2

Total Flow Analysis

Arrival Bounds

$(s_1, \{f_0\}, \emptyset) =: \alpha_{s_1}^{f_0}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \oslash \beta_{s_0}^{l.o.f_0}$		
$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{0,0}$	
$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$	$= \beta_{s_0} = \beta_{20,20}$	
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \oslash \beta_{s_0}^{l.o.f_0}$ $= \gamma_{r_{s_1}^{f_0}, b_{s_1}^{f_0}}$	$r_{s_1}^{f_0}$	$= 5$
	$b_{s_1}^{f_0}$	$= \alpha^{f_0}(T_{s_0}^{l.o.})$
		$= 5 \cdot 20 + 25$
		$= 125$
	$=$	$= \gamma_{5,125}$

$(s_1, \{f_2\}, \emptyset) =: \alpha_{s_1}^{f_2}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_1}^{f_2} = \alpha^{f_2} \oslash \beta_{s_2}^{l.o.f_2}$		
$\alpha_{s_2}^{x(f_2)}$	$\alpha^{f_1} = \gamma_{5,25}$	
$\beta_{s_2}^{l.o.f_2} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_2)}$ $= \beta_{R_{s_2}^{l.o.f_2}, T_{s_2}^{l.o.f_2}}$	$R_{s_2}^{l.o.f_2}$	$[R_{s_2} - r_{s_2}^{x(f_2)}]^+ = 20 - 5$ $= 15$
	$T_{s_2}^{l.o.f_2}$	$\beta_{s_2} = b_{s_2}^{x(f_2)}$ $\beta_{s_2} = \alpha_{s_2}^{x(f_2)}$ $20 \cdot [t - 20]^+ = 25$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 21\frac{1}{4}$ $t = 28\frac{1}{3}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$
	$=$	$= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_1}^{f_2} = \alpha^{f_2} \oslash \beta_{s_2}^{l.o.f_2}$ $= \gamma_{r_{s_1}^{f_2}, b_{s_1}^{f_2}}$	$r_{s_1}^{f_2}$	$= 5$
	$b_{s_1}^{f_2}$	$= \alpha^{f_2}(T_{s_2}^{l.o.f_2})$
		$= 5 \cdot 21\frac{1}{4} + 25$
		$= 131\frac{1}{4}$
	$=$	$= \gamma_{5, 131\frac{1}{4}}$

Analysis

TFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	α_{s_2}	$= \alpha^{f_1} + \alpha^{f_2}$ $= \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{10,50}$	
	$D_{s_2}^{f_2}$	$\beta_{s_2} = b_{s_2}$ $20 \cdot [t - 20]^+ = 50$ $t = 22\frac{1}{2}$	$\beta_{s_2} = \alpha_{s_2}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 50$ $t = 45$
	$B_{s_2}^{f_2}$	$\alpha_{s_2}(T_{s_2}) = 20 \cdot 10 + 50$ $= 250$	
s_1	α_{s_3}	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$ $= \gamma_{5,125} + \gamma_{5,131\frac{1}{4}}$ $= \gamma_{10,256\frac{1}{4}}$	
	$D_{s_1}^{f_2}$	$\beta_{s_1} = b_{s_1}$ $20 \cdot [t - 20]^+ = 256\frac{1}{4}$ $t = 32\frac{13}{16}$	$\beta_{s_1} = \alpha_{s_1}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 291\frac{2}{3}$ $t = 69\frac{1}{6}$
	$B_{s_1}^{f_2}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 256\frac{1}{4}$ $= 456\frac{1}{4}$	
D^{f_2}		$= \sum_{i=1}^2 D_{s_i}^{f_2}$ $= 55\frac{5}{16}$	$= \sum_{i=1}^2 D_{s_i}^{f_2}$ $= 114\frac{1}{6}$
B^{f_2}		$= \max_{i=\{1,2\}} B_{s_i}^{f_2}$ $= 456\frac{1}{4}$	$= \max_{i=\{1,2\}} B_{s_i}^{f_2}$ $= 491\frac{2}{3}$

Separate Flow Analysis and PMOO Analysis

Arrival Bounds


$(s_1, \{f_0\}, f_2) =: \alpha_{s_1}^{f_0}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \oslash \beta_{s_0}^{l.o.f_0}$		
$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{0,0}$	
$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$	$= \beta_{s_0} = \beta_{20,20}$	
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \oslash \beta_{s_0}^{l.o.f_0} = \gamma_{r_{s_1}^{f_0}, b_{s_1}^{f_0}}$	$r_{s_1}^{f_0}$	$= 5$
	$b_{s_1}^{f_0}$	$= \alpha^{f_0}(T_{s_0}^{l.o.})$
		$= 5 \cdot 20 + 25$
		$= 125$
	$=$	$= \gamma_{5,125}$

Analyses

SFA			FIFO Multiplexing	Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_2)}$		$= \alpha^{f_1} = \gamma_{5,25}$	
	$\beta_{s_2}^{l.o.f_2} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_1)}$		$= \beta_{15,21\frac{1}{4}}$	$= \beta_{15,28\frac{1}{3}}$
s_1	$\alpha_{s_1}^{x(f_2)}$		$= \alpha_{s_1}^{f_0} = \gamma_{5,125}$	
	$\beta_{s_1}^{l.o.f_2} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_2)}$ $= \beta_{R_{s_1}^{l.o.f_2}, T_{s_1}^{l.o.f_2}}$	$R_{s_1}^{l.o.f_2}$	$\left[R_{s_1} - r_{s_1}^{x(f_2)}\right]^+ = 20 - 5$ $= 15$	
		$T_{s_1}^{l.o.f_2}$	$\beta_{s_1} = b_{s_1}$ $20 \cdot [t - 20]^+ = 125$ $t = 26\frac{1}{4}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_2)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 125$ $t = 35$
		$=$	$= \beta_{15,26\frac{1}{4}}$	$= \beta_{15,35}$
$\beta_{\langle s_2, s_1 \rangle}^{l.o.f_2} = \beta_{R_{\langle s_2, s_1 \rangle}^{l.o.f_2}, T_{\langle s_2, s_1 \rangle}^{l.o.f_2}}$		$= \bigotimes_{i=1}^2 \beta_{s_i}^{l.o.f_2}$ $= \beta_{15,47\frac{1}{2}}$	$= \bigotimes_{i=1}^2 \beta_{s_i}^{l.o.f_2}$ $= \beta_{15,63\frac{1}{3}}$	
D^{f_2}		$\beta_{e2e}^{l.o.f_2} = b^{f_2}$ $15 \cdot \left[t - 47\frac{1}{2}\right]^+ = 25$ $t = 49\frac{1}{6}$	$\beta_{e2e}^{l.o.f_2} = b^{f_2}$ $15 \cdot \left[t - 63\frac{1}{3}\right]^+ = 25$ $t = 65$	
B^{f_2}		$\alpha^{f_2} \left(T_{e2e}^{l.o.f_2}\right) = 5 \cdot 47\frac{1}{2} + 25$ $= 262\frac{1}{2}$	$\alpha^{f_2} \left(T_{e2e}^{l.o.f_2}\right) = 5 \cdot 63\frac{1}{3} + 25$ $= 341\frac{2}{3}$	

PMOO		Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_2)}$	$= \alpha^{f_1} = \gamma_{5,25}$
	$\alpha_{s_2}^{\bar{x}(f_2)}$	
s_1	$\alpha_{s_1}^{x(f_2)}$	$= \alpha_{s_1}^{f_0} = \gamma_{5,125}$
	$\alpha_{s_1}^{\bar{x}(f_2)}$	
$\beta_{\langle s_2, s_1 \rangle}^{l.o.f_2} = \beta_{R_{\langle s_2, s_1 \rangle}^{l.o.f_2}, T_{\langle s_2, s_1 \rangle}^{l.o.f_2}}$	$R_{\langle s_2, s_1 \rangle}^{l.o.f_2}$	$= \bigwedge_{i \in \{2,1\}} (R_{s_i} - r_{s_i}^{x(f_2)})$ $= (20 - 5) \wedge (20 - 5)$ $= 15$
	$T_{\langle s_2, s_1 \rangle}^{l.o.f_2}$	$= \sum_{i \in \{2,1\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_2)} + r_{s_i}^{x(f_2)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_2}} \right)$ $= 20 + \frac{25 + 5 \cdot 20}{15} + 20 + \frac{125 + 5 \cdot 20}{15}$ $= 40 + \frac{350}{15}$ $= 63\frac{1}{3}$
	$=$	$= \beta_{15, 63\frac{1}{3}}$
D^{f_2}		$\beta_{\langle s_2, s_1 \rangle}^{l.o.f_2} = b^{f_2}$ $15 \cdot \left[t - 63\frac{1}{3} \right]^+ = 25$ $t = 65$
B^{f_2}		$\alpha^{f_2} \left(T_{\langle s_2, s_1 \rangle}^{l.o.f_2} \right) = 5 \cdot 63\frac{1}{3} + 25$ $= 341\frac{2}{3}$

FeedForward_1SC_4Flows_1AC_4Paths



$\mathbb{S} = \{s_0, s_1, s_2, s_3\}$ with

$$\beta_{s_0} = \beta_{s_1} = \beta_{s_2} = \beta_{s_3} = \beta_{R_{s_i}, T_{s_i}} = \beta_{20,20}, \quad i \in \{0, 1, 2, 3\}$$

$\mathbb{F} = \{f_0, f_1, f_2, f_3\}$ with

$$\alpha^{f_n} = \gamma_{r^{f_n}, b^{f_n}} = \gamma_{5,25}, \quad n \in \{0, 1, 2, 3\}$$

Arrival Bounds

$(s_0, \{f_3\}, \emptyset) =: \alpha_{s_0}^{f_3}$ $(s_1, \{f_2\}, \emptyset) =: \alpha_{s_1}^{f_2}$ $(s_3, \{f_1\}, \emptyset) =: \alpha_{s_3}^{f_1}$ $=: \alpha_{s_i}^{f_n}$ with $(n, i) \in \{(3, 0), (2, 1), (1, 3)\}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \odot \beta_{s_2}^{l.o.f_n}$		
$\alpha_{s_2}^{x(f_n)}$	$= \gamma_{5,25} + \gamma_{5,25} = \gamma_{10,50}$	
$\beta_{s_2}^{l.o.f_n} = \beta_{s_2} \ominus \alpha^{x(f_n)}$ $= \beta_{R_{s_2}^{l.o.f_n}, T_{s_2}^{l.o.f_n}}$	$R_{s_2}^{l.o.f_n}$	$\left[R_{s_2} - r_{s_2}^{x(f_n)} \right]^+ = 20 - 5$ $= 15$
	$T_{s_2}^{l.o.f_n}$	$\beta_{s_2} = b_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 50$ $t = 22\frac{1}{2}$
		$\beta_{s_2} = \alpha_{s_2}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 50$ $t = 45$
	$=$	$= \beta_{10,22\frac{1}{2}}$
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \odot \beta_{s_2}^{l.o.f_n}$ $= \gamma_{r_{s_i}^{f_n}, b_{s_i}^{f_n}}$	$r_{s_i}^{f_n}$	$= 5$
	$b_{s_i}^{f_n}$	$\alpha^{f_n} (T_{s_2}^{l.o.f_n}) = 5 \cdot 22\frac{1}{2} + 25 = 137\frac{1}{2}$
	$=$	$= \gamma_{5,137\frac{1}{2}}$
		$\alpha^{f_n} (T_{s_2}^{l.o.f_n}) = 5 \cdot 45 + 25 = 250$
		$= \gamma_{5,250}$

$(s_3, \{f_0\}, \emptyset) = \alpha_{s_1}^{f_0}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \odot \beta_{s_0}^{l.o.f_0}$		
$\alpha_{s_0}^{f_0}$	$= \alpha^{f_0} = \gamma_{5,25}$	
$\alpha_{s_0}^{x(f_0)}$	$= \alpha_{s_0}^{f_3} = \gamma_{5,137\frac{1}{2}}$	$= \alpha_{s_0}^{f_3} = \gamma_{5,250}$
$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha^{x(f_0)}$ $= \beta_{R_{s_0}^{l.o.f_0}, T_{s_0}^{l.o.f_0}}$	$R_{s_0}^{l.o.f_0}$	$\left[R_{s_0} - r_{s_0}^{x(f_0)} \right]^+ = 20 - 5$ $= 15$
	$T_{s_0}^{l.o.f_0}$	$\beta_{s_0} = b_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 137\frac{1}{2}$ $t = 26\frac{7}{8}$
		$\beta_{s_0} = \alpha_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 250$ $t = 43\frac{1}{3}$
	$=$	$= \beta_{15,26\frac{7}{8}}$
$\alpha_{s_1}^{f_0} = \alpha^{f_0} \odot \beta_{s_0}^{l.o.f_0}$ $= \gamma_{r_{s_1}^{f_0}, b_{s_1}^{f_0}}$	$r_{s_1}^{f_0}$	$= 5$
	$b_{s_1}^{f_0}$	$\alpha^{f_0} (T_{s_0}^{l.o.f_0}) = 5 \cdot 26\frac{7}{8} + 25 = 159\frac{3}{8}$
	$=$	$= \gamma_{5,159\frac{3}{8}}$
		$\alpha^{f_0} (T_{s_0}^{l.o.f_0}) = 5 \cdot 43\frac{1}{3} + 25 = 241\frac{2}{3}$
		$= \gamma_{5,241\frac{2}{3}}$

$(s_3, \{f_0\}, \emptyset) = \alpha_{s_3}^{f_0}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_3}^{f_0} = \alpha^{f_0} \odot (\beta_{s_0}^{l.o.f_0} \otimes \beta_{s_1}^{l.o.f_0})$ (reuse of previous result) $= \alpha^{f_0} \odot \beta_{s_0}^{l.o.f_0} \odot \beta_{s_1}^{l.o.f_0}$ $= \alpha_{s_1}^{f_0} \odot \beta_{s_1}^{l.o.f_0}$		
$\alpha_{s_1}^{f_0}$	$= \gamma_{5,159\frac{3}{8}}$	$= \gamma_{5,241\frac{2}{3}}$
$\alpha_{s_1}^{x(f_0)}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,137\frac{1}{2}}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,250}$
$\beta_{s_1}^{l.o.f_0} = \beta_{s_1} \otimes \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{l.o.f_0}, T_{s_1}^{l.o.f_0}}$	$R_{s_1}^{l.o.f_0}$	$\left[R_{s_1} - r_{s_1}^{x(f_0)} \right]^+ = 20 - 5$ $= 15$
	$T_{s_1}^{l.o.f_0}$	$\beta_{s_1} = b_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 137\frac{1}{2}$ $t = 26\frac{7}{8}$
		$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 250$ $t = 43\frac{1}{3}$
	$=$	$= \beta_{15,26\frac{7}{8}}$
$\alpha_{s_3}^{f_0} = \alpha_{s_1}^{f_0} \odot \beta_{s_1}^{l.o.f_0}$ $= \gamma_{r_{s_3}^{f_0}, b_{s_3}^{f_0}}$	$r_{s_3}^{f_0}$	$= 5$
	$b_{s_3}^{f_0}$	$\alpha_{s_1}^{f_0} (T_{s_1}^{l.o.f_0}) = 5 \cdot 26\frac{7}{8} + 159\frac{3}{8} = 293\frac{3}{4}$
	$=$	$= \gamma_{5,293\frac{3}{4}}$
		$\alpha_{s_1}^{f_0} (T_{s_1}^{l.o.f_0}) = 5 \cdot 43\frac{1}{3} + 241\frac{2}{3} = 458\frac{1}{3}$
		$= \gamma_{5,458\frac{1}{3}}$

$(s_3, \{f_3\}, \emptyset) = \alpha_{s_3}^{f_3}$		FIFO Multiplexing	Arbitrary Multiplexing
PbooArrivalBound_Concatenation.java			
$\begin{aligned} \alpha_{s_3}^{f_3} &= \alpha_{s_0}^{f_3} \odot (\beta_{s_2}^{l.o.f_3} \otimes \beta_{s_0}^{l.o.f_3}) \\ &\quad (\text{reuse of previous result}) \\ &= \alpha_{s_0}^{f_3} \odot \beta_{s_2}^{l.o.f_3} \odot \beta_{s_0}^{l.o.f_3} \\ &= \alpha_{s_0}^{f_3} \odot \beta_{s_0}^{l.o.f_3} \end{aligned}$			
$\alpha_{s_0}^{x(f_3)}$		$= \alpha^{f_0} = \gamma_{5,25}$	
$\begin{aligned} \beta_{s_0}^{l.o.f_3} &= \beta_{s_0} \ominus \alpha_{s_0}^{x(f_3)} \\ &= \beta_{R_{s_0}^{l.o.f_3}, T_{s_0}^{l.o.f_3}} \end{aligned}$	$R_{s_0}^{l.o.f_3}$	$\begin{aligned} [R_{s_0} - r_{s_0}^{x(f_3)}]^+ &= 20 - 5 \\ &= 15 \end{aligned}$	
	$T_{s_0}^{l.o.f_3}$	$\begin{aligned} \beta_{s_0} &= b_{s_0}^{f_0} \\ 20 \cdot [t - 20]^+ &= 25 \\ t &= 21\frac{1}{4} \end{aligned}$	$\begin{aligned} \beta_{s_0} &= \alpha^{f_0} \\ 20 \cdot [t - 20]^+ &= 5 \cdot t + 25 \\ t &= 28\frac{1}{3} \end{aligned}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_0}^{f_3}$		$= \gamma_{5, 137\frac{1}{2}}$	$= \gamma_{5, 250}$
$\begin{aligned} \alpha_{s_3}^{f_3} &= \alpha_{s_0}^{f_3} \odot \beta_{s_0}^{l.o.f_3} \\ &= \gamma_{r_{s_3}^{f_3}, b_{s_3}^{f_3}} \end{aligned}$	$r_{s_3}^{f_3}$	$= 5$	
	$b_{s_3}^{f_3}$	$\begin{aligned} &= \alpha_{s_0}^{f_3} (T_{s_0}^{l.o.f_3}) \\ &= 5 \cdot 21\frac{1}{4} + 137\frac{1}{2} \\ &= 243\frac{3}{4} \end{aligned}$	$\begin{aligned} &= \alpha_{s_0}^{f_3} (T_{s_0}^{l.o.f_3}) \\ &= 5 \cdot 28\frac{1}{3} + 250 \\ &= 391\frac{2}{3} \end{aligned}$
	$=$	$= \gamma_{5, 243\frac{3}{4}}$	$= \gamma_{5, 391\frac{2}{3}}$
PmooArrivalBound.java			
$\alpha_{s_3}^{f_3} = \alpha^{f_3} \odot \beta_{\langle s_2, s_0 \rangle}^{l.o.f_3}$			
s_2	$\alpha_{s_2}^{x(f_3)}$		$= \alpha^{f_1} + \alpha^{f_2}$
	$\bar{\alpha}_{s_2}^{x(f_3)}$		$= \gamma_{5, 25} + \gamma_{5, 25}$
s_0	$\alpha_{s_0}^{x(f_3)}$		$\equiv \alpha^{f_0} = \gamma_{5, 25}^{10, 50}$
	$\bar{\alpha}_{s_0}^{x(f_3)}$		
$\beta_{\langle s_2, s_0 \rangle}^{l.o.f_3} = \beta_{R_{\langle s_2, s_0 \rangle}^{l.o.f_3}, T_{\langle s_2, s_0 \rangle}^{l.o.f_3}}$	$R_{\langle s_2, s_0 \rangle}^{l.o.f_3}$		$\begin{aligned} &= \bigwedge_{i \in \{2, 0\}} (R_{s_i} - r_{s_i}^{x(f_3)}) \\ &= (20 - 10) \wedge (20 - 5) \\ &= 10 \end{aligned}$
	$T_{\langle s_2, s_0 \rangle}^{l.o.f_3}$		$\begin{aligned} &= \sum_{i \in \{2, 0\}} \left(T_{s_i} + \frac{b_{s_i}^{x(f_3)} + r_{s_i}^{x(f_3)} \cdot T_{s_i}}{R_{\langle s_2, s_0 \rangle}^{l.o.f_3}} \right) \\ &= 20 + \frac{50 + 10 \cdot 20}{10} + 20 + \frac{25 + 5 \cdot 20}{10} \\ &= 77\frac{1}{2} \end{aligned}$
	$=$		$= \beta_{10, 77\frac{1}{2}}$
$\alpha_{s_3}^{f_3} = \alpha^{f_3} \odot \beta_{\langle s_2, s_0 \rangle}^{l.o.f_3}$	$r_{s_3}^{f_3}$		$= 5$
	$b_{s_3}^{f_3}$		$\begin{aligned} &= \alpha_{s_0}^{f_3} (T_{\langle s_2, s_0 \rangle}^{l.o.f_3}) \\ &= 5 \cdot 77\frac{1}{2} + 25 \\ &= 412\frac{1}{2} \end{aligned}$
	$=$		$= \gamma_{5, 412\frac{1}{2}}$

Flow f_0

Total Flow Analysis

Analysis

TFA		FIFO Multiplexing	Arbitrary Multiplexing	
		PbooArrivalBound_Concatenation.java	PmooArrivalBound.java	
s_0	α_{s_0}	$= \alpha_{s_0}^{f_0} + \alpha_{s_0}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,137\frac{1}{2}}$ $= \gamma_{10,162\frac{1}{2}}$	$= \alpha_{s_0}^{f_0} + \alpha_{s_0}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,250}$ $= \gamma_{10,275}$	
	$D_{s_0}^{f_0}$	$\beta_{s_0} = b_{s_0}$ $20 \cdot [t - 20]^+ = 162\frac{1}{2}$ $t = 28\frac{1}{8}$	$\beta_{s_0} = \alpha_{s_0}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 275$ $t = 67\frac{1}{2}$	
	$B_{s_0}^{f_0}$	$\alpha_{s_0}(T_{s_0}) = 10 \cdot 20 + 162\frac{1}{2}$ $= 262\frac{1}{2}$	$\alpha_{s_0}(T_{s_0}) = 10 \cdot 20 + 275$ $= 475$	
s_1	α_{s_1}	$= \alpha_{s_1}^{f_0} + \alpha_{s_1}^{f_2}$ $= \gamma_{5,159\frac{3}{8}} + \gamma_{5,137\frac{1}{2}}$ $= \gamma_{10,296\frac{7}{8}}$	$= \alpha_{s_1}^{f_0} + \alpha_{s_1}^{f_2}$ $= \gamma_{5,241\frac{2}{3}} + \gamma_{5,250}$ $= \gamma_{10,491\frac{2}{3}}$	
	$D_{s_1}^{f_0}$	$\beta_{s_1} = b_{s_1}$ $20 \cdot [t - 20]^+ = 296\frac{7}{8}$ $t = 34\frac{27}{32}$	$\beta_{s_1} = \alpha_{s_1}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 491\frac{2}{3}$ $t = 89\frac{1}{6}$	
	$B_{s_1}^{f_0}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 296\frac{7}{8}$ $= 496\frac{7}{8}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 491\frac{2}{3}$ $= 691\frac{2}{3}$	
s_3	α_{s_3}	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,293\frac{3}{4}} + \gamma_{5,137\frac{1}{2}} + \gamma_{5,243\frac{3}{4}}$ $= \gamma_{15,675}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,458\frac{1}{3}} + \gamma_{5,250} + \gamma_{5,391\frac{2}{3}}$ $= \gamma_{15,1100}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,458\frac{1}{3}} + \gamma_{5,250} + \gamma_{5,412\frac{1}{2}}$ $= \gamma_{15,1120\frac{5}{6}}$
	$D_{s_3}^{f_0}$	$\beta_{s_3} = b_{s_3}$ $20 \cdot [t - 20]^+ = 675$ $t = 53\frac{3}{4}$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 1100$ $t = 300$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 1120\frac{5}{6}$ $t = 304\frac{1}{6}$
	$B_{s_3}^{f_0}$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 675$ $= 975$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 1100$ $= 1400$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 1120\frac{5}{6}$ $= 1420\frac{5}{6}$
D^{f_0}		$D_{s_0}^{f_0} + D_{s_1}^{f_0} + D_{s_3}^{f_0} = 116\frac{23}{32}$	$D_{s_0}^{f_0} + D_{s_1}^{f_0} + D_{s_3}^{f_0} = 456\frac{2}{3}$	
B^{f_0}		$\max\{B_{s_0}^{f_0}, B_{s_1}^{f_0}, B_{s_3}^{f_0}\} = 975$	$\max\{B_{s_0}^{f_0}, B_{s_1}^{f_0}, B_{s_3}^{f_0}\} = 1400$	
			$\max\{B_{s_0}^{f_0}, B_{s_1}^{f_0}, B_{s_3}^{f_0}\} = 1420\frac{5}{6}$	

Separate Flow Analysis and PMOO Analysis

Analyses

PbooArrivalBound_Concatenation.java

SFA			FIFO Multiplexing	Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$		$= \alpha_{s_0}^{f_3} = \gamma_{5,137\frac{1}{2}}$	$= \alpha_{s_0}^{f_3} = \gamma_{5,250}$
	$\beta_{s_0}^{1.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_3)}$ $= \beta_{R_{s_0}^{1.o.f_0}, T_{s_0}^{1.o.f_0}}$	$R_{s_0}^{1.o.f_0}$	$\left[R_{s_0} - r_{s_0}^{x(f_0)}\right]^+ = 15$	
		$T_{s_0}^{1.o.f_0}$	$\beta_{s_0} = b_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 137\frac{1}{2}$ $t = 26\frac{7}{8}$	$\beta_{s_0} = \alpha_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 250$ $t = 43\frac{1}{3}$
		$=$	$= \beta_{15,26\frac{7}{8}}$	$= \beta_{15,43\frac{1}{3}}$
s_1	$\alpha_{s_1}^{x(f_0)}$		$= \alpha_{s_1}^{f_1} = \gamma_{5,137\frac{1}{2}}$	$= \alpha_{s_1}^{f_1} = \gamma_{5,250}$
	$\beta_{s_1}^{1.o.f_0} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{1.o.f_0}, T_{s_1}^{1.o.f_0}}$	$R_{s_1}^{1.o.f_0}$	$\left[R_{s_1} - r_{s_1}^{x(f_0)}\right]^+ = 15$	
		$T_{s_1}^{1.o.f_0}$	$\beta_{s_1} = b_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 137\frac{1}{2}$ $t = 26\frac{7}{8}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 250$ $t = 43\frac{1}{3}$
		$=$	$= \beta_{15,26\frac{7}{8}}$	$= \beta_{15,43\frac{1}{3}}$
s_3	$\alpha_{s_3}^{x(f_0)}$		$= \alpha_{s_3}^{f_2} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,137\frac{1}{2}} + \gamma_{5,243\frac{3}{4}}$ $= \gamma_{10,381\frac{1}{4}}$	$= \alpha_{s_3}^{f_2} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,250} + \gamma_{5,391\frac{2}{3}}$ $= \gamma_{10,641\frac{2}{3}}$
	$\beta_{s_3}^{1.o.f_0} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_0)}$ $= \beta_{R_{s_3}^{1.o.f_0}, T_{s_3}^{1.o.f_0}}$	$R_{s_3}^{1.o.f_0}$	$\left[R_{s_3} - r_{s_3}^{x(f_0)}\right]^+ = 10$	
		$T_{s_3}^{1.o.f_0}$	$\beta_{s_3} = b_{s_3}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 381\frac{1}{4}$ $t = 39\frac{1}{16}$	$\beta_{s_3} = \alpha_{s_3}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 641\frac{2}{3}$ $t = 104\frac{1}{6}$
		$=$	$= \beta_{10,39\frac{1}{16}}$	$= \beta_{10,104\frac{1}{6}}$
$\beta_{e2e}^{1.o.f_0} = \beta_{R_{e2e}^{1.o.f_0}, T_{e2e}^{1.o.f_0}}$			$\bigotimes_{i=\{0,1,3\}} \beta_{s_i}^{1.o.f_0} = \beta_{10,92\frac{13}{16}}$	$\bigotimes_{i=\{0,1,3\}} \beta_{s_i}^{1.o.f_0} = \beta_{10,190\frac{5}{6}}$
D^{f_0}			$\beta_{e2e}^{1.o.f_0} = b^{f_0}$ $10 \cdot \left[t - 92\frac{13}{16}\right]^+ = 25$ $t = 95\frac{5}{16}$	$\beta_{e2e}^{1.o.f_0} = b^{f_0}$ $10 \cdot \left[t - 190\frac{5}{6}\right]^+ = 25$ $t = 193\frac{1}{3}$
B^{f_0}			$\alpha^{f_0} \left(T_{e2e}^{1.o.f_0}\right) = 5 \cdot 92\frac{13}{16} + 25$ $= 489\frac{1}{16}$	$\alpha^{f_0} \left(T_{e2e}^{1.o.f_0}\right) = 5 \cdot 190\frac{5}{6} + 25$ $= 979\frac{1}{6}$

SFA			Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$		$= \alpha_{s_0}^{f_3} = \gamma_{5,250}$
	$\beta_{s_0}^{l.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_3)}$ $= \beta_{R_{s_0}^{l.o.f_0}, T_{s_0}^{l.o.f_0}}$	$R_{s_0}^{l.o.f_0}$	$\left[R_{s_0} - r_{s_0}^{x(f_0)} \right]^+ = 15$
		$T_{s_0}^{l.o.f_0}$	$\beta_{s_0} = \alpha_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 250$ $t = 43\frac{1}{3}$
		$=$	$= \beta_{15, 43\frac{1}{3}}$
s_1	$\alpha_{s_1}^{x(f_0)} = \alpha_{s_1}^{f_1}$		$= \gamma_{5,250}$
	$\beta_{s_1}^{l.o.f_0} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_0)}$ $= \beta_{R_{s_1}^{l.o.f_0}, T_{s_1}^{l.o.f_0}}$	$R_{s_1}^{l.o.f_0}$	$\left[R_{s_1} - r_{s_1}^{x(f_0)} \right]^+ = 15$
		$T_{s_1}^{l.o.f_0}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 250$ $t = 43\frac{1}{3}$
		$=$	$= \beta_{15, 43\frac{1}{3}}$
s_3	$\alpha_{s_3}^{x(f_0)} = \alpha_{s_3}^{f_2} + \alpha_{s_3}^{f_3}$		$= \gamma_{5,250} + \gamma_{5,412\frac{1}{2}} = \gamma_{10,662\frac{1}{2}}$
	$\beta_{s_3}^{l.o.f_0} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_0)}$ $= \beta_{R_{s_3}^{l.o.f_0}, T_{s_3}^{l.o.f_0}}$	$R_{s_3}^{l.o.f_0}$	$\left[R_{s_3} - r_{s_3}^{x(f_0)} \right]^+ = 10$
		$T_{s_3}^{l.o.f_0}$	$\beta_{s_3} = \alpha_{s_3}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 662\frac{1}{2}$ $t = 106\frac{1}{4}$
		$=$	$= \beta_{10, 106\frac{1}{4}}$
$\beta_{e2e}^{l.o.f_0} = \beta_{R_{e2e}^{l.o.f_0}, T_{e2e}^{l.o.f_0}}$			$\bigotimes_{i=\{0,1,3\}} \beta_{s_i}^{l.o.f_0} = \beta_{10, 192\frac{11}{12}}$
D^{f_0}			$\beta_{e2e}^{l.o.f_0} = b^{f_0}$ $10 \cdot \left[t - 192\frac{11}{12} \right]^+ = 25$ $t = 195\frac{5}{12}$
B^{f_0}			$\alpha^{f_0} \left(T_{e2e}^{l.o.f_0} \right) = 5 \cdot 192\frac{11}{12} + 25$ $= 989\frac{7}{12}$

PMOO		Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$	$= \alpha_{s_0}^{f_3} = \gamma_{5,250}$
	$\alpha_{s_0}^{\bar{x}(f_0)}$	
s_1	$\alpha_{s_1}^{x(f_0)}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,250}$
	$\alpha_{s_1}^{\bar{x}(f_0)}$	
s_3	$\alpha_{s_3}^{x(f_0)}$	$= \alpha_{s_3}^{f_2} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,250} + \gamma_{5,391\frac{2}{3}}$
	$\alpha_{s_3}^{\bar{x}(f_0)}$	
$\beta_{e2e}^{l.o.f_0} = \beta_{R_{e2e}^{l.o.f_0}, T_{e2e}^{l.o.f_0}}$	$R_{e2e}^{l.o.f_0}$	$= \bigwedge_{i \in \{0,1,3\}} (R_{s_i}^{l.o.f_0} \wedge r_{s_i}^{x(f_0)})$ $= (20 - 5) \wedge (20 - 5) \wedge (20 - 10)$ $= 10$
	$T_{e2e}^{l.o.f_0}$	$= \sum_{i \in \{0,1,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_0)} + r_{s_i}^{x(f_0)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_0}} \right)$ $= 20 + \frac{250 + 5 \cdot 20}{10} + 20 + \frac{250 + 5 \cdot 20}{10} + 20 + \frac{641\frac{2}{3} + 10 \cdot 20}{10}$ $= 60 + \frac{1541\frac{2}{3}}{10}$ $= 214\frac{1}{6}$
	$=$	$= \beta_{10, 214\frac{1}{6}}$
D^{f_0}		$\beta_{e2e}^{l.o.f_0} = b^{f_0}$ $10 \cdot \left[t - 214\frac{1}{6} \right]^+ = 25$ $t = 216\frac{2}{3}$
B^{f_0}		$\alpha^{f_0} (T_{e2e}^{l.o.f_0}) = 5 \cdot 214\frac{1}{6} + 25$ $= 1095\frac{5}{6}$

PMOO		Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$	$= \alpha_{s_0}^{f_3} = \gamma_{5,250}$
	$\alpha_{s_0}^{\bar{x}(f_0)}$	
s_1	$\alpha_{s_1}^{x(f_0)}$	$= \alpha_{s_1}^{f_2} = \gamma_{5,250}$
	$\alpha_{s_1}^{\bar{x}(f_0)}$	
s_3	$\alpha_{s_3}^{x(f_0)}$	$= \alpha_{s_3}^{f_2} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,250} + \gamma_{5,412\frac{1}{2}}$
	$\alpha_{s_3}^{\bar{x}(f_0)}$	
$\beta_{e2e}^{l.o.f_0} = \beta_{R_{e2e}^{l.o.f_0}, T_{e2e}^{l.o.f_0}}$	$R_{e2e}^{l.o.f_0}$	$= \bigwedge_{i \in \{0,1,3\}} \gamma_{\left(R_{e2e}^{l.o.f_0} + r_{s_i}^{x(f_0)}\right)}$ $= (20 - 5) \wedge (20 - 5) \wedge (20 - 10)$ $= 10$
	$T_{e2e}^{l.o.f_0}$	$= \sum_{i \in \{0,1,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_0)} + r_{s_i}^{x(f_0)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_0}} \right)$ $= 20 + \frac{250 + 5 \cdot 20}{10} + 20 + \frac{250 + 5 \cdot 20}{10} + 20 + \frac{662\frac{1}{2} + 10 \cdot 20}{10}$ $= 60 + \frac{1462\frac{1}{2}}{10}$ $= 216\frac{1}{4}$
	$=$	$= \beta_{10, 216\frac{1}{4}}$
D^{f_0}		$\beta_{e2e}^{l.o.f_0} = b^{f_0}$ $10 \cdot \left[t - 216\frac{1}{4} \right]^+ = 25$ $t = 218\frac{3}{4}$
B^{f_0}		$\alpha^{f_0} \left(T_{e2e}^{l.o.f_0} \right) = 5 \cdot 216\frac{1}{4} + 25$ $= 1106\frac{1}{4}$

Flow f_1

Total Flow Analysis

Analysis

PbooArrivalBound_Concatenation.java

TFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	α_{s_2}	$\begin{aligned}\alpha_{s_3}^{f_3} &= \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_3} \\ &= \gamma_{5,25} + \gamma_{5,25} + \gamma_{5,25} \\ &= \gamma_{15,75}\end{aligned}$	
	$D_{s_2}^{f_1}$	$\begin{aligned}\beta_{s_2} &= b_{s_2} \\ 20 \cdot [t - 20]^+ &= 75 \\ t &= 23\frac{3}{4}\end{aligned}$	$\begin{aligned}\beta_{s_2} &= \alpha_{s_2} \\ 20 \cdot [t - 20]^+ &= 15 \cdot t + 75 \\ t &= 95\end{aligned}$
	$B_{s_2}^{f_1}$	$\begin{aligned}\alpha_{s_2}(T_{s_2}) &= 15 \cdot 20 + 75 \\ &= 375\end{aligned}$	
s_3	α_{s_3}	$\begin{aligned}&= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3} \\ &= \gamma_{5,137\frac{1}{2}} + \gamma_{5,293\frac{3}{4}} + \gamma_{5,243\frac{3}{4}} \\ &= \gamma_{15,675}\end{aligned}$	$\begin{aligned}&= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3} \\ &= \gamma_{5,250} + \gamma_{5,458\frac{1}{3}} + \gamma_{5,391\frac{2}{3}} \\ &= \gamma_{15,1100}\end{aligned}$
	$D_{s_3}^{f_1}$	$\begin{aligned}\beta_{s_3} &= b_{s_3} \\ 20 \cdot [t - 20]^+ &= 675 \\ t &= 53\frac{3}{4}\end{aligned}$	$\begin{aligned}\beta_{s_3} &= \alpha_{s_3} \\ 20 \cdot [t - 20]^+ &= 15 \cdot t + 1100 \\ t &= 300\end{aligned}$
	$B_{s_3}^{f_1}$	$\begin{aligned}\alpha_{s_3}(T_{s_3}) &= 15 \cdot 20 + 675 \\ &= 975\end{aligned}$	$\begin{aligned}\alpha_{s_3}(T_{s_3}) &= 15 \cdot 20 + 1100 \\ &= 1400\end{aligned}$
$D_{s_2}^{f_1}$		$D_{s_2}^{f_1} + D_{s_3}^{f_1} = 77\frac{1}{2}$	$D_{s_2}^{f_1} + D_{s_3}^{f_1} = 395$
$B_{s_2}^{f_1}$		$\max\{B_{s_2}^{f_1}, B_{s_3}^{f_1}\} = 975$	$\max\{B_{s_2}^{f_1}, B_{s_3}^{f_1}\} = 1400$

TFA		Arbitrary Multiplexing
s_2	α_{s_2}	$\alpha_{s_3}^{f_3} = \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{15,75}$
	$D_{s_2}^{f_1}$	$\beta_{s_2} = \alpha_{s_2}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 75$ $t = 95$
	$B_{s_2}^{f_1}$	$\alpha_{s_2}(T_{s_2}) = 15 \cdot 20 + 75$ $= 375$
s_3	α_{s_3}	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,250} + \gamma_{5,458\frac{1}{3}} + \gamma_{5,412\frac{1}{2}}$ $= \gamma_{15,1120\frac{5}{6}}$
	$D_{s_3}^{f_1}$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 1120\frac{5}{6}$ $t = 304\frac{1}{6}$
	$B_{s_3}^{f_1}$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 1120\frac{5}{6}$ $= 1420\frac{5}{6}$
D^{f_1}		$D_{s_2}^{f_1} + D_{s_3}^{f_1} = 399\frac{1}{6}$
B^{f_1}		$\max\{B_{s_2}^{f_1}, B_{s_3}^{f_1}\} = 1420\frac{5}{6}$

Separate Flow Analysis and PMOO Analysis

Analyses

PbooArrivalBound_Concatenation.java

SFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_1)}$	$= \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{10,50}$	
	$\beta_{s_2}^{l.o.f_1} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_1)}$	$= \beta_{10,22\frac{1}{2}}$	$= \beta_{10,45}$
s_3	$\alpha_{s_3}^{x(f_1)}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,293\frac{3}{4}} + \gamma_{5,243\frac{3}{4}}$ $= \gamma_{10,537\frac{1}{3}}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,458\frac{1}{3}} + \gamma_{5,391\frac{2}{3}}$ $= \gamma_{10,850}$
	$\beta_{s_3}^{l.o.f_1} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_1)}$	$[R_{s_3} - r_{s_3}^{x(f_1)}]^+ = 10$	
	$= \beta_{R_{s_3}^{l.o.f_1}, T_{s_3}^{l.o.f_1}}$	$\beta_{s_3} = b_{s_3}^{x(f_1)}$ $20 \cdot [t - 20]^+ = 537\frac{1}{2}$ $t = 46\frac{7}{8}$	$\beta_{s_3} = \alpha_{s_3}^{x(f_1)}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 850$ $t = 125$
		$=$	$=$
		$= \beta_{10,46\frac{7}{8}}$	$= \beta_{10,125}$
$\beta_{e2e}^{l.o.f_1} = \beta_{R_{e2e}^{l.o.f_1}, T_{e2e}^{l.o.f_1}}$		$\bigotimes_{i=2}^3 \beta_{s_i}^{l.o.f_1} = \beta_{10,69\frac{3}{8}}$	$\bigotimes_{i=2}^3 \beta_{s_i}^{l.o.f_1} = \beta_{10,170}$
D^{f_1}		$\beta_{e2e}^{l.o.f_1} = b^{f_1}$ $10 \cdot \left[t - 69\frac{3}{8} \right]^+ = 25$ $t = 71\frac{7}{8}$	$\beta_{e2e}^{l.o.f_1} = b^{f_1}$ $10 \cdot [t - 170]^+ = 25$ $t = 172\frac{1}{2}$
B^{f_1}		$\alpha^{f_1} \left(T_{e2e}^{l.o.f_1} \right) = 5 \cdot 69\frac{3}{8} + 25$ $= 371\frac{7}{8}$	$\alpha^{f_1} \left(T_{e2e}^{l.o.f_1} \right) = 5 \cdot 170 + 25$ $= 875$

SFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_1)}$		$= \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{10,50}$
	$\beta_{s_2}^{l.o.f_1} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_1)}$		$= \beta_{10,45}$
s_3	$\alpha_{s_3}^{x(f_1)}$		$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,458\frac{1}{3}} + \gamma_{5,412\frac{1}{2}}$ $= \gamma_{10,870\frac{5}{6}}$
	$\beta_{s_3}^{l.o.f_1} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_1)}$	$R_{s_3}^{l.o.f_1}$	$\left[R_{s_3} - r_{s_3}^{x(f_1)} \right]^+ = 10$
	$= \beta_{R_{s_3}^{l.o.f_1}, T_{s_3}^{l.o.f_1}}$		$\beta_{s_3} = \alpha_{s_3}^{x(f_1)}$
	$T_{s_3}^{l.o.f_1}$		$20 \cdot [t - 20]^+ = 10 \cdot t + 870\frac{5}{6}$ $t = 127\frac{1}{12}$
	$=$		$= \beta_{10,127\frac{1}{12}}$
$\beta_{e2e}^{l.o.f_1} = \beta_{R_{e2e}^{l.o.f_1}, T_{e2e}^{l.o.f_1}}$			$\bigotimes_{i=2}^3 \beta_{s_i}^{l.o.f_1} = \beta_{10,172\frac{1}{12}}$
D^{f_1}			$\beta_{e2e}^{l.o.f_1} = b^{f_1}$ $10 \cdot \left[t - 172\frac{1}{12} \right]^+ = 25$ $t = 174\frac{7}{12}$
B^{f_1}			$\alpha^{f_1} \left(T_{e2e}^{l.o.f_1} \right) = 5 \cdot 172\frac{1}{12} + 25$ $= 885\frac{5}{12}$

PMOO		Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_1)}$	$= \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_3}$
	$\alpha_{s_2}^{\bar{x}(f_1)}$	$= \gamma_{5,25} + \gamma_{5,25}$
s_3	$\alpha_{s_3}^{x(f_1)}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_3}$
	$\alpha_{s_3}^{\bar{x}(f_1)}$	$= \gamma_{5,458\frac{1}{3}} + \gamma_{5,391\frac{2}{3}}$
$\beta_{e2e}^{l.o.f_1} = \beta_{R_{e2e}^{l.o.f_1}, T_{e2e}^{l.o.f_1}}$	$R_{e2e}^{l.o.f_1}$	$= \bigwedge_{i \in \{2,3\}} (R_{s_i} - \gamma_{10,850}^{x(f_1)})$ $= (20 - 10) \wedge (20 - 10)$ $= 10$
	$T_{e2e}^{l.o.f_1}$	$= \sum_{i \in \{2,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_1)} + r_{s_i}^{x(f_1)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_1}} \right)$ $= 20 + \frac{50 + 10 \cdot 20}{10} + 20 + \frac{850 + 10 \cdot 20}{10}$ $= 40 + \frac{1300}{10}$ $= 170$
	$=$	$= \beta_{10,170}$
D^{f_1}		$\beta_{e2e}^{l.o.f_1} = b^{f_1}$ $10 \cdot [t - 170]^+ = 25$ $t = 172\frac{1}{2}$
B^{f_1}		$\alpha^{f_1} (T_{e2e}^{l.o.f_1}) = 5 \cdot 170 + 25$ $= 875$

PMOO		Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_1)}$	$= \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_3}$
	$\alpha_{s_2}^{\bar{x}(f_1)}$	$= \gamma_{5,25} + \gamma_{5,25}$
s_3	$\alpha_{s_3}^{x(f_1)}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_3}$
	$\alpha_{s_3}^{\bar{x}(f_1)}$	$= \gamma_{5,458\frac{1}{3}} + \gamma_{5,412\frac{1}{2}}$
$\beta_{e2e}^{l.o.f_1} = \beta_{R_{e2e}^{l.o.f_1}, T_{e2e}^{l.o.f_1}}$	$R_{e2e}^{l.o.f_1}$	$= \bigwedge_{i \in \{2,3\}} \left(R_{s_i} \gamma_{10,870\frac{5}{6}}^{x(f_1)} \right)$ $= (20 - 10) \wedge (20 - 10)$ $= 10$
	$T_{e2e}^{l.o.f_1}$	$= \sum_{i \in \{2,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_1)} + r_{s_i}^{x(f_1)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_1}} \right)$ $= 20 + \frac{50 + 10 \cdot 20}{10} + 20 + \frac{870\frac{5}{6} + 10 \cdot 20}{10}$ $= 40 + \frac{1320\frac{5}{6}}{10}$ $= 172\frac{1}{12}$
	$=$	$= \beta_{10,172\frac{1}{12}}$
D^{f_1}		$\beta_{e2e}^{l.o.f_1} = b^{f_1}$ $10 \cdot \left[t - 172\frac{1}{12} \right]^+ = 25$ $t = 174\frac{7}{12}$
B^{f_1}		$\alpha^{f_1} \left(T_{e2e}^{l.o.f_1} \right) = 5 \cdot 172\frac{1}{12} + 25$ $= 885\frac{5}{12}$

Flow f_2

Total Flow Analysis

Analysis

TFA		FIFO Multiplexing	Arbitrary Multiplexing
s_2	α_{s_2}	$= \alpha_{s_2}^{f_2} + \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{15,75}$	
	$D_{s_2}^{f_2}$	$\beta_{s_2} = b_{s_2}$ $20 \cdot [t - 20]^+ = 75$ $t = 23\frac{3}{4}$	$\beta_{s_2} = \alpha_{s_2}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 75$ $t = 95$
	$B_{s_2}^{f_2}$	$\alpha_{s_2}(T_{s_2}) = 15 \cdot 20 + 75$	$= 375$
s_1	α_{s_1}	$= \alpha_{s_1}^{f_2} + \alpha_{s_1}^{f_0}$ $= \gamma_{5,137\frac{1}{2}} + \gamma_{5,159\frac{3}{8}}$ $= \gamma_{10,296\frac{7}{8}}$	$= \alpha_{s_1}^{f_2} + \alpha_{s_1}^{f_0}$ $= \gamma_{5,250} + \gamma_{5,241\frac{2}{3}}$ $= \gamma_{10,491\frac{2}{3}}$
	$D_{s_1}^{f_2}$	$\beta_{s_1} = b_{s_1}$ $20 \cdot [t - 20]^+ = 296\frac{7}{8}$ $t = 34\frac{27}{32}$	$\beta_{s_1} = \alpha_{s_1}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 491\frac{2}{3}$ $t = 89\frac{1}{6}$
	$B_{s_1}^{f_2}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 296\frac{7}{8}$ $= 496\frac{7}{8}$	$\alpha_{s_1}(T_{s_1}) = 10 \cdot 20 + 491\frac{2}{3}$ $= 691\frac{2}{3}$
D^{f_2}		$D_{s_2}^{f_2} + D_{s_1}^{f_2} = 58\frac{19}{32}$	$D_{s_2}^{f_2} + D_{s_1}^{f_2} = 184\frac{1}{6}$
B^{f_2}		$\max\{B_{s_2}^{f_2}, B_{s_1}^{f_2}\} = 496\frac{7}{8}$	$\max\{B_{s_2}^{f_2}, B_{s_1}^{f_2}\} = 691\frac{2}{3}$

Separate Flow Analysis and PMOO Analysis

Analyses

SFA			FIFO Multiplexing	Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_2)}$		$= \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{10,50}$	
	$\beta_{s_2}^{l.o.f_2} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_2)}$		$= \beta_{10,22\frac{1}{2}}$	$= \beta_{10,45}$
s_1	$\alpha_{s_1}^{x(f_2)}$		$= \alpha_{s_1}^{f_0} = \gamma_{5,159\frac{3}{8}}$	$= \alpha_{s_1}^{f_0} = \gamma_{5,241\frac{2}{3}}$
	$\beta_{s_1}^{l.o.f_2} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_2)}$ $= \beta_{R_{s_1}^{l.o.f_2}, T_{s_1}^{l.o.f_2}}$	$R_{s_1}^{l.o.f_2}$	$[R_{s_2} - r_{s_2}^{x(f_2)}]^+ = 15$	
		$T_{s_1}^{l.o.f_2}$	$\beta_{s_1} = b_{s_1}^{x(f_2)}$ $20 \cdot [t - 20]^+ = 159\frac{3}{8}$ $t = 27\frac{31}{32}$	$\beta_{s_1} = \alpha_{s_1}^{x(f_2)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 241\frac{2}{3}$ $t = 42\frac{7}{9}$
		$=$	$= \beta_{10,27\frac{31}{32}}$	$= \beta_{10,42\frac{7}{9}}$
$\beta_{e2e}^{l.o.f_2} = \beta_{R_{e2e}^{l.o.f_2}, T_{e2e}^{l.o.f_2}}$			$\bigotimes_{i=1}^2 \beta_{s_i}^{l.o.f_2} = \beta_{10,50\frac{15}{32}}$	$\bigotimes_{i=1}^2 \beta_{s_i}^{l.o.f_2} = \beta_{10,87\frac{7}{9}}$
D^{f_2}			$\beta_{e2e}^{l.o.f_2} = b^{f_2}$ $10 \cdot \left[t - 50\frac{15}{32}\right]^+ = 25$ $t = 52\frac{31}{32}$	$\beta_{e2e}^{l.o.f_2} = b^{f_2}$ $10 \cdot \left[t - 87\frac{7}{9}\right]^+ = 25$ $t = 90\frac{5}{18}$
B^{f_2}			$\alpha^{f_2} \left(T_{e2e}^{l.o.f_2}\right) = 5 \cdot 50\frac{15}{32} + 25$ $= 277\frac{11}{32}$	$\alpha^{f_2} \left(T_{e2e}^{l.o.f_2}\right) = 5 \cdot 87\frac{7}{9} + 25$ $= 463\frac{8}{9}$

PMOO		Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_2)}$	$= \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_3}$
	$\alpha_{s_2}^{\bar{x}(f_2)}$	$= \gamma_{5,25} + \gamma_{5,25}$
s_1	$\alpha_{s_1}^{x(f_2)}$	$\equiv \alpha_{s_1}^{f_0} = \gamma_{5,241\frac{50}{3}}$
	$\alpha_{s_1}^{\bar{x}(f_2)}$	
$\beta_{e2e}^{l.o.f_2} = \beta_{R_{e2e}^{l.o.f_2}, T_{e2e}^{l.o.f_2}}$	$R_{e2e}^{l.o.f_2}$	$= \bigwedge_{i \in \{2,1\}} (R_{s_i} - r_{s_i}^{x(f_2)})$ $= (20 - 10) \wedge (20 - 5)$ $= 10$
	$T_{e2e}^{l.o.f_2}$	$= \sum_{i \in \{2,1\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_2)} + r_{s_i}^{x(f_2)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_2}} \right)$ $= 20 + \frac{50 + 10 \cdot 20}{10} + 20 + \frac{241\frac{2}{3} + 5 \cdot 20}{10}$ $= 40 + \frac{591\frac{2}{3}}{10}$ $= 99\frac{1}{6}$
	$=$	$= \beta_{10,99\frac{1}{6}}$
D^{f_2}		$\beta_{e2e}^{l.o.f_2} = b^{f_2}$ $10 \cdot \left[t - 99\frac{1}{6} \right] = 25$ $t = 101\frac{2}{3}$
B^{f_2}		$\alpha^{f_2} (T_{e2e}^{l.o.f_2}) = 5 \cdot 99\frac{1}{6} + 25$ $= 520\frac{5}{6}$

Flow f_3

Total Flow Analysis

Analysis

PbooArrivalBound_Concatenation.java

TFA		FIFO Multiplexing	Arbitrary Multiplexing	
		PbooArrivalBound_Concatenation.java		PmooArrivalBound.java
s_2	α_{s_2}	$= \alpha_{s_2}^{f_3} + \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_2}$ $= \gamma_{5,25} + \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{15,75}$		
	$D_{s_2}^{f_3}$	$\beta_{s_2} = b_{s_2}$ $20 \cdot [t - 20]^+ = 75$ $t = 23\frac{3}{4}$	$\beta_{s_2} = \alpha_{s_2}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 75$ $t = 95$	
	$B_{s_2}^{f_3}$	$\alpha_{s_2}(T_{s_2}) = 15 \cdot 20 + 75$ $= 375$		
s_0	α_{s_0}	$= \alpha_{s_0}^{f_0} + \alpha_{s_0}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,137\frac{1}{2}}$ $= \gamma_{10,162\frac{1}{2}}$	$= \alpha_{s_0}^{f_0} + \alpha_{s_0}^{f_3}$ $= \gamma_{5,25} + \gamma_{5,250}$ $= \gamma_{10,275}$	
	$D_{s_0}^{f_3}$	$\beta_{s_0} = b_{s_0}$ $20 \cdot [t - 20]^+ = 162\frac{1}{2}$ $t = 28\frac{1}{8}$	$\beta_{s_0} = \alpha_{s_0}$ $20 \cdot [t - 20]^+ = 10 \cdot t + 275$ $t = 67\frac{1}{2}$	
	$B_{s_0}^{f_3}$	$\alpha_{s_0}(T_{s_0}) = 10 \cdot 20 + 162\frac{1}{2}$ $= 262\frac{1}{2}$	$\alpha_{s_0}(T_{s_0}) = 10 \cdot 20 + 275$ $= 475$	
s_3	α_{s_3}	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,293\frac{3}{4}} + \gamma_{5,137\frac{1}{2}} + \gamma_{5,243\frac{3}{4}}$ $= \gamma_{15,675}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,458\frac{1}{3}} + \gamma_{5,250} + \gamma_{5,391\frac{2}{3}}$ $= \gamma_{15,1100}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1} + \alpha_{s_3}^{f_3}$ $= \gamma_{5,458\frac{1}{3}} + \gamma_{5,250} + \gamma_{5,412\frac{1}{2}}$ $= \gamma_{15,1120\frac{5}{6}}$
	$D_{s_3}^{f_3}$	$\beta_{s_3} = b_{s_3}$ $20 \cdot [t - 20]^+ = 675$ $t = 53\frac{3}{4}$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 1100$ $t = 300$	$\beta_{s_3} = \alpha_{s_3}$ $20 \cdot [t - 20]^+ = 15 \cdot t + 1120\frac{5}{6}$ $t = 304\frac{1}{6}$
	$B_{s_3}^{f_3}$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 675$ $= 975$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 1100$ $= 1400$	$\alpha_{s_3}(T_{s_3}) = 15 \cdot 20 + 1120\frac{5}{6}$ $= 1420\frac{5}{6}$
D^{f_3}		$D_{s_2}^{f_3} + D_{s_0}^{f_3} + D_{s_3}^{f_3} = 105\frac{5}{8}$	$D_{s_2}^{f_3} + D_{s_0}^{f_3} + D_{s_3}^{f_3} = 462\frac{1}{2}$	$D_{s_2}^{f_3} + D_{s_0}^{f_3} + D_{s_3}^{f_3} = 466\frac{2}{3}$
B^{f_3}		$\max\{B_{s_2}^{f_3}, B_{s_0}^{f_3}, B_{s_3}^{f_3}\} = 975$	$\max\{B_{s_2}^{f_3}, B_{s_0}^{f_3}, B_{s_3}^{f_3}\} = 1400$	$\max\{B_{s_2}^{f_3}, B_{s_0}^{f_3}, B_{s_3}^{f_3}\} = 1420\frac{5}{6}$


Separate Flow Analysis and PMOO Analysis

Analyses

SFA			FIFO Multiplexing	Arbitrary Multiplexing
s_2	$\alpha_{s_2}^{x(f_3)}$		$= \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_2}$	
	$\beta_{s_2}^{l.o.f_3} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_3)}$		$= \gamma_{5,25} + \gamma_{5,25}$	
			$= \gamma_{10,50}$	
s_0	$\alpha_{s_0}^{x(f_3)}$		$= \alpha_{s_0}^{f_0} = \gamma_{5,25}$	
	$\beta_{s_0}^{l.o.f_3} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_3)}$		$= \beta_{15,22\frac{1}{2}}$	$= \beta_{15,28\frac{1}{3}}$
s_3	$\alpha_{s_3}^{x(f_3)}$		$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$
			$= \gamma_{5,293\frac{3}{4}} + \gamma_{5,137\frac{1}{2}}$	$= \gamma_{5,458\frac{1}{3}} + \gamma_{5,250}$
			$= \gamma_{10,431\frac{1}{4}}$	$= \gamma_{10,708\frac{1}{3}}$
	$\beta_{s_3}^{l.o.f_3} = \beta_{s_3} \ominus \alpha_{s_3}^{x(f_3)}$	$R_{s_3}^{l.o.f_3}$	$[R_{s_3} - r_{s_3}^{x(f_3)}]^+ = 10$	
	$= \beta_{R_{s_3}^{l.o.f_3}, T_{s_3}^{l.o.f_3}}$	$T_{s_3}^{l.o.f_3}$	$\beta_{s_3} = b_{s_3}^{x(f_3)}$	$\beta_{s_3} = \alpha_{s_3}^{x(f_3)}$
			$20 \cdot [t - 20]^+ = 431\frac{1}{4}$	$20 \cdot [t - 20]^+ = 10 \cdot t + 708\frac{1}{3}$
			$t = 41\frac{9}{16}$	$t = 110\frac{5}{6}$
		$=$	$= \beta_{10,41\frac{9}{16}}$	$= \beta_{10,110\frac{5}{6}}$
$\beta_{e2e}^{l.o.f_3} = \beta_{R_{e2e}^{l.o.f_3}, T_{e2e}^{l.o.f_3}}$			$\bigotimes_{i=\{2,0,3\}} \beta_{s_i}^{l.o.f_3} = \beta_{10,85\frac{5}{16}}$	$\bigotimes_{i=\{2,0,3\}} \beta_{s_i}^{l.o.f_3} = \beta_{10,184\frac{1}{6}}$
D^{f_3}			$\beta_{e2e}^{l.o.f_3} = b^{f_3}$	$\beta_{e2e}^{l.o.f_3} = b^{f_3}$
			$10 \cdot \left[t - 85\frac{5}{16} \right]^+ = 25$	$10 \cdot \left[t - 184\frac{1}{6} \right]^+ = 25$
			$t = 87\frac{13}{16}$	$t = 186\frac{2}{3}$
B^{f_3}			$\alpha^{f_3} \left(T_{e2e}^{l.o.f_3} \right) = 5 \cdot 85\frac{5}{16} + 25$	$\alpha^{f_3} \left(T_{e2e}^{l.o.f_3} \right) = 5 \cdot 184\frac{1}{6} + 25$
			$= 451\frac{9}{16}$	$= 945\frac{5}{6}$

PMOO		Arbitrary Multiplexing	
s_2	$\alpha_{s_2}^{x(f_3)}$	$= \alpha_{s_2}^{f_1} + \alpha_{s_2}^{f_2}$	
	$\alpha_{s_2}^{\bar{x}(f_3)}$	$= \gamma_{5,25} + \gamma_{5,25}$	
s_0	$\alpha_{s_0}^{x(f_3)}$	$\equiv \alpha_{s_0}^{f_0} = \gamma_{5,25}^{10,50}$	
	$\alpha_{s_0}^{\bar{x}(f_3)}$		
s_3	$\alpha_{s_3}^{x(f_3)}$	$= \alpha_{s_3}^{f_0} + \alpha_{s_3}^{f_1}$	
	$\alpha_{s_3}^{\bar{x}(f_3)}$	$= \gamma_{5,458\frac{1}{3}} + \gamma_{5,250}$	
$\beta_{e2e}^{l.o.f_3} = \beta_{R_{e2e}^{l.o.f_3}, T_{e2e}^{l.o.f_3}}$	$R_{e2e}^{l.o.f_3}$	$= = \bigwedge_{i \in \{2,0,3\}} \gamma_{10, 108\frac{1}{3}}^{R_{e2e}^{l.o.f_3} - r_{s_i}^{x(f_3)}}$ $= (20 - 10) \wedge (20 - 5) \wedge (20 - 10)$ $= 10$	
	$T_{e2e}^{l.o.f_3}$	$= \sum_{i \in \{2,0,3\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_3)} + r_{s_i}^{x(f_3)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_3}} \right)$ $= 20 + \frac{50 + 10 \cdot 20}{10} + 20 + \frac{25 + 5 \cdot 20}{10} + 20 + \frac{708\frac{1}{3} + 10 \cdot 20}{10}$ $= 60 + \frac{1283\frac{1}{3}}{10}$ $= 188\frac{1}{3}$	
	$=$	$= \beta_{10, 188\frac{1}{3}}$	
D^{f_3}		$\beta_{e2e}^{l.o.f_3} = b^{f_3}$ $10 \cdot \left[t - 188\frac{1}{3} \right]^+ = 25$ $t = 190\frac{5}{6}$	
B^{f_3}		$\alpha^{f_3} \left(T_{e2e}^{l.o.f_3} \right) = 5 \cdot 188\frac{1}{3} + 25$ $= 966\frac{2}{3}$	

FeedForward_1SC_2Flows_1AC_2Paths



$\mathbb{S} = \{s_0, s_1, s_2\}$ with

$$\beta_{s_0} = \beta_{s_1} = \beta_{s_2} = \beta_{R_{s_i}, T_{s_i}} = \beta_{20,20}, \quad i \in \{0, 1, 2\}$$

$\mathbb{F} = \{f_0, f_1\}$ with

$$\alpha^{f_0} = \alpha^{f_1} = \gamma_{r^{f_n}, b^{f_n}} = \gamma_{5,25}, \quad n \in \{0, 1\}$$

Flow f_0

Total Flow Analysis

Arrival Bounds

$(s_1, \{f_1\}, \emptyset) =: \alpha_{s_1}^{f_1}$ $(s_2, \{f_0\}, \emptyset) =: \alpha_{s_2}^{f_0}$ $=: \alpha_{s_i}^{f_n}$ with $(n, i) \in \{(1, 1), (0, 2)\}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \circ \beta_{s_0}^{l.o.f_n}$		
$\alpha_{s_0}^{x(f_n)}$	$= \gamma_{5,25}$	
$\beta_{s_0}^{l.o.f_n} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_n)}$	$R_{s_0}^{l.o.f_n}$	$= 15$
$= \beta_{R_{s_0}^{l.o.f_n}, T_{s_0}^{l.o.f_n}}$	$T_{s_0}^{l.o.f_n}$	$\beta_{s_0} = b_{s_0}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$ $= \beta_{15, 21\frac{1}{4}}$
	$=$	$\beta_{s_0} = \alpha_{s_0}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$ $= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \circ \beta_{s_0}^{l.o.f_n}$	$r_{s_i}^{f_n}$	$= 5$
$= \gamma_{r_{s_i}^{f_n}, b_{s_i}^{f_n}}$	$b_{s_i}^{f_n}$	$\alpha^{f_0}(T_{s_0}^{l.o.f_n}) = 5 \cdot 21\frac{1}{4} + 25$ $= 131\frac{1}{4}$ $= \gamma_{5, 131\frac{1}{4}}$
	$=$	$\alpha^{f_0}(T_{s_0}^{l.o.f_n}) = 5 \cdot 28\frac{1}{3} + 25$ $= 166\frac{2}{3}$ $= \gamma_{5, 166\frac{2}{3}}$

$(s_2, \{f_1\}, \emptyset) =: \alpha_{s_2}^{f_1}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_2}^{f_1} = \alpha^{f_1} \circ (\beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}^{l.o.f_1})$ (reuse of previous result) $= \alpha^{f_1} \circ \beta_{s_0}^{l.o.f_1} \circ \beta_{s_1}^{l.o.f_1}$ $= \alpha_{s_1}^{f_1} \circ \beta_{s_1}^{l.o.f_1}$		
$\alpha_{s_1}^{x(f_1)}$	$= \gamma_{0,0}$	
$\beta_{s_1}^{l.o.f_1} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_1)}$	$= \beta_{s_1} = \beta_{20,20}$	
$\alpha_{s_1}^{f_1}$	$= \gamma_{5, 131\frac{1}{4}}$	$= \gamma_{5, 166\frac{2}{3}}$
$\alpha_{s_2}^{f_1} = \alpha^{f_1} \circ \beta_{s_1}^{l.o.f_1}$	$r_{s_2}^{f_1}$	$= 5$
$= \gamma_{r_{s_2}^{f_1}, b_{s_2}^{f_1}}$	$b_{s_2}^{f_1}$	$\alpha^{f_0}(T_{s_0}^{l.o.f_0}) = 5 \cdot 20 + 131\frac{1}{4}$ $= 231\frac{1}{4}$ $= \gamma_{5, 231\frac{1}{4}}$
	$=$	$\alpha^{f_0}(T_{s_0}^{l.o.f_0}) = 5 \cdot 20 + 166\frac{2}{3}$ $= 266\frac{2}{3}$ $= \gamma_{5, 266\frac{2}{3}}$

Remark:

PmooArrivalBound.java will have the same result as PbooArrivalBound_Concatenation.java because f_0 does not have cross-traffic interfering on multiple consecutive hops.

Analysis

TFA	FIFO Multiplexing	Arbitrary Multiplexing
s_0	α_{s_0}	$= \alpha^{f_0} + \alpha^{f_1}$ $= \gamma_{5,25} + \gamma_{5,25}$ $= \gamma_{10,50}$
	$D_{s_0}^{f_0}$	$\beta_{s_0} = b_{s_0}$ $20 \cdot [t - 20]^+ = 50$ $t = 22\frac{1}{2}$
	$B_{s_0}^{f_0}$	$\alpha_{s_0}(T_{s_0}) = 10 \cdot 20 + 50$ $= 250$
s_2	α_{s_2}	$= \alpha_{s_2}^{f_0} + \alpha_{s_2}^{f_1}$ $= \gamma_{5,231\frac{1}{4}} + \gamma_{5,131\frac{1}{4}}$ $= \gamma_{10,362\frac{1}{2}}$
	$D_{s_2}^{f_0}$	$\beta_{s_2} = b_{s_2}$ $20 \cdot [t - 20]^+ = 362\frac{1}{2}$ $t = 38\frac{1}{8}$
	$B_{s_2}^{f_0}$	$\alpha_{s_2}(T_{s_2}) = 10 \cdot 20 + 362\frac{1}{2}$ $= 562\frac{1}{2}$
D^{f_0}	$\sum_{i=\{0,2\}} D_{s_i}^{f_0} = 60\frac{5}{8}$	$\sum_{i=\{0,2\}} D_{s_i}^{f_0} = 128\frac{1}{3}$
B^{f_0}	$\max_{i=\{0,2\}} B_{s_i}^{f_0} = 562\frac{1}{2}$	$\max_{i=\{0,2\}} B_{s_i}^{f_0} = 633\frac{1}{3}$

Separate Flow Analysis and PMOO Analysis

Arrival Bounds

$(s_2, \{f_1\}, f_0) =: \alpha_{s_2}^{f_1}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_2}^{f_1} = \alpha^{f_1} \odot (\beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}^{l.o.f_1})$		
$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{5,25}$	
$\beta_{s_0}^{l.o.f_1} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_1)}$	$= 15$	
$= \beta_{R_{s_0}^{l.o.f_1}, T_{s_0}^{l.o.f_1}}$	$\beta_{s_0} = b_{s_0}^{x(f_1)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$	$\beta_{s_0} = \alpha_{s_0}^{x(f_1)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$
$=$	$= \beta_{15,21\frac{1}{4}}$	$= \beta_{15,28\frac{1}{3}}$
$\alpha_{s_1}^{x(f_1)}$	$= \gamma_{0,0}$	
$\beta_{s_1}^{l.o.f_1} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_1)}$	$= \beta_{s_1} = \beta_{20,20}$	
$\beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}^{l.o.f_1} = \beta_{\langle s_0, s_1 \rangle}^{l.o.f_1}$	$= \beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}$	$= \beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}$
$= \beta_{R_{\langle s_0, s_1 \rangle}^{l.o.f_1}, T_{\langle s_0, s_1 \rangle}^{l.o.f_1}}$	$= \beta_{15,21\frac{1}{4}} \otimes \beta_{20,20}$	$= \beta_{15,28\frac{1}{3}} \otimes \beta_{20,20}$
	$= \beta_{15,41\frac{1}{4}}$	$= \beta_{15,48\frac{1}{3}}$
$\alpha_{s_2}^{f_1} = \alpha^{f_1} \odot (\beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}^{l.o.f_1})$	$= 5$	
$= \gamma_{r_{\langle s_0, s_1 \rangle}^{f_1}, b_{\langle s_0, s_1 \rangle}^{f_1}}$	$\alpha^{f_1}(T_{\langle s_0, s_1 \rangle}^{l.o.f_1}) = 5 \cdot 41\frac{1}{4} + 25$ $= 231\frac{1}{4}$	$\alpha^{f_1}(T_{\langle s_0, s_1 \rangle}^{l.o.f_1}) = 5 \cdot 48\frac{1}{3} + 25$ $= 266\frac{2}{3}$
$=$	$= \gamma_{5,231\frac{1}{4}}$	$= \gamma_{5,266\frac{2}{3}}$

Remark:

PmooArrivalBound.java will have the same result as PbooArrivalBound_Concatenation.java because f_0 does not have cross-traffic interfering on multiple consecutive hops.

Analyses

SFA			FIFO Multiplexing	Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$		$= \alpha^{f_1} = \gamma_{5,25}$	
	$\beta_{s_0}^{1.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$ $= \beta_{R_{s_0}^{1.o.f_0}, T_{s_0}^{1.o.f_0}}$	$R_{s_0}^{1.o.f_0}$	$\left[R_{s_0} - r_{s_0}^{x(f_0)} \right]^+ = 15$	
		$T_{s_0}^{1.o.f_0}$	$\beta_{s_0} = b_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$	$\beta_{s_0} = \alpha_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$
		$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
s_2	$\alpha_{s_2}^{x(f_0)}$		$= \gamma_{5, 231\frac{1}{4}}$	$= \gamma_{5, 266\frac{2}{3}}$
	$\beta_{s_2}^{1.o.f_0} = \beta_{s_2} \ominus \alpha_{s_2}^{x(f_0)}$ $= \beta_{R_{s_2}^{1.o.f_0}, T_{s_2}^{1.o.f_0}}$	$R_{s_2}^{1.o.f_0}$	$\left[R_{s_2} - r_{s_2}^{x(f_0)} \right]^+ = 15$	
		$T_{s_2}^{1.o.f_0}$	$\beta_{s_2} = b_{s_2}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 231\frac{1}{4}$ $t = 31\frac{9}{16}$	$\beta_{s_2} = \alpha_{s_2}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 266\frac{2}{3}$ $t = 44\frac{4}{9}$
		$=$	$= \beta_{15, 31\frac{9}{16}}$	$= \beta_{15, 44\frac{4}{9}}$
$\beta_{e2e}^{1.o.f_0} = \beta_{R_{e2e}^{1.o.f_0}, T_{e2e}^{1.o.f_0}}$			$\bigotimes_{i=\{0,2\}} \beta_{s_i}^{1.o.f_0} = \beta_{15, 52\frac{13}{16}}$	$\bigotimes_{i=\{0,2\}} \beta_{s_i}^{1.o.f_0} = \beta_{15, 72\frac{7}{9}}$
D^{f_0}			$\beta_{e2e}^{1.o.f_0} = b^{f_0}$ $15 \cdot \left[t - 52\frac{13}{16} \right]^+ = 25$ $t = 54\frac{23}{48}$	$\beta_{e2e}^{1.o.f_0} = b^{f_0}$ $15 \cdot \left[t - 72\frac{7}{9} \right]^+ = 25$ $t = 74\frac{4}{9}$
B^{f_0}			$\alpha^{f_0} \left(T_{e2e}^{1.o.f_0} \right) = 5 \cdot 52\frac{13}{16} + 25$ $= 289\frac{1}{16}$	$\alpha^{f_0} \left(T_{e2e}^{1.o.f_0} \right) = 5 \cdot 72\frac{7}{9} + 25$ $= 388\frac{8}{9}$

PMOO		Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{5,25}$
	$\bar{\alpha}_{s_0}^{x(f_0)}$	
	$\alpha_{s_0}^{x(f_0)}$	
s_2	$\alpha_{s_2}^{x(f_0)}$	$= \gamma_{5, 266\frac{2}{3}}$
	$\bar{\alpha}_{s_2}^{x(f_0)}$	
	$\alpha_{s_2}^{x(f_0)}$	
$\beta_{e2e}^{1.o.f_0} = \beta_{R_{e2e}^{1.o.f_0}, T_{e2e}^{1.o.f_0}}$	$R_{e2e}^{1.o.f_0}$	$= \bigwedge_{i \in \{0,2\}} \left(R_{s_i} - r_{s_i}^{x(f_0)} \right)$ $= (20 - 5) \wedge (20 - 5)$ $= 15$
	$T_{e2e}^{1.o.f_0}$	$= \sum_{i \in \{0,2\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_0)} + r_{s_i}^{x(f_0)} \cdot T_{s_i}}{R_{e2e}^{1.o.f_0}} \right)$ $= 20 + \frac{25 + 5 \cdot 20}{15} + 20 + \frac{266\frac{2}{3} + 5 \cdot 20}{15}$ $= 40 + \frac{491\frac{2}{3}}{15}$ $= 72\frac{7}{9}$
	$=$	$= \beta_{15, 72\frac{7}{9}}$
	$\beta_{e2e}^{1.o.f_0} = b^{f_0}$	
	$15 \cdot \left[t - 72\frac{7}{9} \right]^+ = 25$ $t = 74\frac{4}{9}$	
B^{f_0}		$\alpha^{f_0} \left(T_{e2e}^{1.o.f_0} \right) = 5 \cdot 72\frac{7}{9} + 25$ $= 388\frac{8}{9}$

Flow f_1

Total Flow Analysis

Arrival Bounds

$(s_1, \{f_1\}, \emptyset) =: \alpha_{s_1}^{f_1}$ $(s_2, \{f_0\}, \emptyset) =: \alpha_{s_2}^{f_0}$ $=: \alpha_{s_i}^{f_n}$ with $(n, i) \in \{(1, 1), (0, 2)\}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \odot \beta_{s_0}^{l.o.f_n}$		
$\alpha_{s_0}^{x(f_n)}$	$= \gamma_{5,25}$	
$\beta_{s_0}^{l.o.f_n} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_n)}$	$R_{s_0}^{l.o.f_n}$	$= 15$
$= \beta_{R_{s_0}^{l.o.f_n}, T_{s_0}^{l.o.f_n}}$	$T_{s_0}^{l.o.f_n}$	$\beta_{s_0} = b_{s_0}^{x(f_n)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$ $20 \cdot [t - 20]^+ = 5 \cdot t + 25$ $t = 28\frac{1}{3}$
$=$	$= \beta_{15, 21\frac{1}{4}}$	$= \beta_{15, 28\frac{1}{3}}$
$\alpha_{s_i}^{f_n} = \alpha^{f_n} \odot \beta_{s_0}^{l.o.f_n}$	$r_{s_i}^{f_n}$	$= 5$
	$b_{s_i}^{f_n}$	$\alpha^{f_0} (T_{s_0}^{l.o.f_n}) = 131\frac{1}{4}$
	$=$	$\alpha^{f_0} (T_{s_0}^{l.o.f_n}) = 166\frac{2}{3}$
		$= \gamma_{5, 131\frac{1}{4}}$
		$= \gamma_{5, 166\frac{2}{3}}$

$(s_2, \{f_1\}, \emptyset) =: \alpha_{s_2}^{f_1}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_2}^{f_1} = \alpha^{f_1} \odot (\beta_{s_0}^{l.o.f_1} \otimes \beta_{s_1}^{l.o.f_1}) = \alpha^{f_1} \odot \beta_{s_0}^{l.o.f_1} \odot \beta_{s_1}^{l.o.f_1} = \alpha_{s_1}^{f_1} \odot \beta_{s_1}^{l.o.f_1}$		
$\alpha_{s_1}^{x(f_1)}$	$= \gamma_{0,0}$	
$\beta_{s_1}^{l.o.f_1} = \beta_{s_1} \ominus \alpha_{s_1}^{x(f_1)}$	$= \beta_{s_1} = \beta_{20,20}$	
$\alpha_{s_1}^{f_1}$	$= \gamma_{5, 131\frac{1}{4}}$	$= \gamma_{5, 166\frac{2}{3}}$
$\alpha_{s_2}^{f_1} = \alpha_{s_1}^{f_1} \odot \beta_{s_1}^{l.o.f_1}$	$r_{s_2}^{f_1}$	$= 5$
$= \alpha_{s_1}^{f_1} \odot \beta_{s_1}^{l.o.f_1}$	$b_{s_2}^{f_1}$	$\alpha^{f_0} (T_{s_0}^{l.o.f_0}) = 231\frac{1}{4}$
$=$	$=$	$\alpha^{f_0} (T_{s_0}^{l.o.f_0}) = 266\frac{2}{3}$
	$= \gamma_{5, 231\frac{1}{4}}$	$= \gamma_{5, 266\frac{2}{3}}$

Remark:

`PmooArrivalBound.java` will have the same result as `PbooArrivalBound_Concatenation.java` because f_1 does not have cross-traffic interfering on multiple consecutive hops.

Analysis

TFA	FIFO Multiplexing	Arbitrary Multiplexing
s_0	α_{s_0}	$= \alpha^{f_0} + \alpha^{f_1} = \gamma_{5,25} + \gamma_{5,25} = \gamma_{10,50}$
	$D_{s_0}^{f_0}$	$\beta_{s_0} = b_{s_0}$ $20 \cdot [t - 20]^+ = 50$ $t = 22\frac{1}{2}$
	$B_{s_0}^{f_0}$	$\alpha_{s_0}(T_{s_0}) = 10 \cdot 20 + 50 = 250$
s_1	α_{s_1}	$= \alpha_{s_1}^{f_1} = \gamma_{5,131\frac{1}{4}}$
	$D_{s_1}^{f_1}$	$\beta_{s_1} = b_{s_1}$ $20 \cdot [t - 20]^+ = 131\frac{1}{4}$ $t = 26\frac{9}{16}$
	$B_{s_1}^{f_1}$	$\alpha_{s_1}(T_{s_1}) = 5 \cdot 20 + 131\frac{1}{4} = 231\frac{1}{4}$
s_2	α_{s_2}	$= \alpha_{s_2}^{f_0} + \alpha_{s_2}^{f_1} = \gamma_{5,231\frac{1}{4}} + \gamma_{5,131\frac{1}{4}} = \gamma_{10,362\frac{1}{2}}$
	$D_{s_2}^{f_1}$	$\beta_{s_2} = b_{s_2}$ $20 \cdot [t - 20]^+ = 362\frac{1}{2}$ $t = 38\frac{1}{8}$
	$B_{s_2}^{f_1}$	$\alpha_{s_2}(T_{s_2}) = 10 \cdot 20 + 362\frac{1}{2} = 562\frac{1}{2}$
D^{f_1}	$\sum_{i=0}^2 \beta_{s_i}^{f_1} = 87\frac{3}{16}$	
B^{f_1}	$\max_{i=0}^2 B_{s_i}^{f_1} = 562\frac{1}{2}$	

Separate Flow Analysis and PMOO Analysis

Arrival Bounds

$(s_2, \{f_0\}, \emptyset) =: \alpha_{s_2}^{f_0}$	FIFO Multiplexing	Arbitrary Multiplexing
$\alpha_{s_2}^{f_0} = \alpha^{f_0} \odot \beta_{s_0}^{1.o.f_0}$		
$\alpha_{s_0}^{x(f_0)}$	$= \gamma_{5,25}$	
$\beta_{s_0}^{1.o.f_0} = \beta_{s_0} \ominus \alpha_{s_0}^{x(f_0)}$	$R_{s_0}^{1.o.f_0}$	$= 15$
$= \beta_{R_{s_0}^{1.o.f_0}, T_{s_0}^{1.o.f_0}}$	$T_{s_0}^{1.o.f_0}$	$\beta_{s_0} = b_{s_0}^{x(f_0)}$ $20 \cdot [t - 20]^+ = 25$ $t = 21\frac{1}{4}$
	$=$	$= \beta_{15, 21\frac{1}{4}}$
$\alpha_{s_2}^{f_0} = \alpha^{f_0} \odot \beta_{s_2}^{1.o.f_0}$	$r_{s_2}^{f_0}$	$= 5$
$= \alpha^{f_0} \odot \beta_{s_2}^{1.o.f_0}$	$b_{s_2}^{f_0}$	$\alpha^{f_0}(T_{s_0}^{1.o.f_0}) = 131\frac{1}{4}$
	$=$	$= \gamma_{5,131\frac{1}{4}}$

Remark:

`PmooArrivalBound.java` will have the same result as `PbooArrivalBound_Concatenation.java` because f_1 does not have cross-traffic interfering on multiple consecutive hops.

Analyses

SFA		FIFO Multiplexing	Arbitrary Multiplexing	
s ₀	α _{s₀} ^{x(f₁)}		= α ^{f₀} = γ _{5,25}	
	β _{s₀} ^{l.o.f₁} = β _{s₀} ⊖ α _{s₀} ^{x(f₁)}	R _{s₀} ^{l.o.f₁}	$\left[R_{s_0} - r_{s_0}^{x(f_1)}\right]^+ = 15$	
		T _{s₀} ^{l.o.f₁}	$\begin{aligned} \beta_{s_0} &= b_{s_0}^{x(f_1)} & \beta_{s_0} &= \alpha_{s_0}^{x(f_1)} \\ 20 \cdot [t - 20]^+ &= 25 & 20 \cdot [t - 20]^+ &= 5 \cdot t + 25 \\ t &= 21\frac{1}{4} & t &= 28\frac{1}{3} \end{aligned}$	
		=	= β _{15,21¹₄}	= β _{15,28¹₃}
s ₁	α _{s₁} ^{x(f₁)}		= γ _{0,0}	
	β _{s₁} ^{l.o.f₁} = β _{s₁} ⊖ α _{s₁} ^{x(f₁)}		= β _{s₁} = β _{20,20}	
s ₂	α _{s₂} ^{x(f₁)}		$\begin{aligned} &= \gamma_{5,131\frac{1}{4}} & &= \gamma_{5,166\frac{2}{3}} \end{aligned}$	
	β _{s₂} ^{l.o.f₁} = β _{s₂} ⊖ α _{s₂} ^{x(f₁)}	R _{s₂} ^{l.o.f₁}	$\left[R_{s_2} - r_{s_2}^{x(f_1)}\right]^+ = 15$	
		T _{s₂} ^{l.o.f₁}	$\begin{aligned} \beta_{s_2} &= b_{s_2}^{x(f_1)} & \beta_{s_2} &= \alpha_{s_2}^{x(f_1)} \\ 20 \cdot [t - 20]^+ &= 131\frac{1}{4} & 20 \cdot [t - 20]^+ &= 5 \cdot t + 166\frac{2}{3} \\ t &= 26\frac{9}{16} & t &= 37\frac{7}{9} \end{aligned}$	
		=	= β _{15,26⁹₁₆}	= β _{15,37⁷₉}
		β _{e2e} ^{l.o.f₁} = β _{R_{e2e}^{l.o.f₁}, T_{e2e}^{l.o.f₁}}		⊗ _{i=0} ² β _{s_i} ^{l.o.f₁} = β _{15,67¹³₁₆}
D ^{f₁}		$\begin{aligned} \beta_{e2e}^{l.o.f_1} &= b^{f_1} \\ 15 \cdot \left[t - 67\frac{13}{16}\right]^+ &= 25 \\ t &= 69\frac{23}{48} \end{aligned}$	$\begin{aligned} \beta_{e2e}^{l.o.f_1} &= b^{f_1} \\ 15 \cdot \left[t - 86\frac{1}{9}\right]^+ &= 25 \\ t &= 87\frac{7}{9} \end{aligned}$	
B ^{f₁}		$\begin{aligned} \alpha^{f_1} \left(T_{e2e}^{l.o.f_1}\right) &= 5 \cdot 67\frac{13}{16} + 25 \\ &= 364\frac{1}{16} \end{aligned}$	$\begin{aligned} \alpha^{f_1} \left(T_{e2e}^{l.o.f_1}\right) &= 5 \cdot 86\frac{1}{9} + 25 \\ &= 455\frac{5}{9} \end{aligned}$	

PMOO		Arbitrary Multiplexing
s_0	$\alpha_{s_0}^{x(f_1)}$	$= \gamma_{5,25}$
	$\alpha_{s_0}^{\bar{x}(f_1)}$	
s_1	$\alpha_{s_0}^{x(f_1)}$	$= \gamma_{0,0}$
	$\alpha_{s_0}^{\bar{x}(f_1)}$	
s_2	$\alpha_{s_2}^{x(f_1)}$	$= \gamma_{5,166\frac{2}{3}}$
	$\alpha_{s_2}^{\bar{x}(f_1)}$	
$\beta_{e2e}^{l.o.f_1} = \beta_{R_{e2e}^{l.o.f_1}, T_{e2e}^{l.o.f_1}}$	$R_{e2e}^{l.o.f_1}$	$= \bigwedge_{i \in \{0,1,2\}} \left(R_{s_i} - r_{s_i}^{x(f_1)} \right)$ $= (20 - 5) \wedge (20 - 0) \wedge (20 - 5)$ $= 15$
	$T_{e2e}^{l.o.f_3}$	$= \sum_{i \in \{0,1,2\}} \left(T_{s_i} + \frac{b_{s_i}^{\bar{x}(f_1)} + r_{s_i}^{x(f_1)} \cdot T_{s_i}}{R_{e2e}^{l.o.f_1}} \right)$ $= 20 + \frac{25 + 5 \cdot 20}{15} + 20 + \frac{0 + 0 \cdot 20}{15} + 20 + \frac{166\frac{2}{3} + 5 \cdot 20}{15}$ $= 60 + \frac{391\frac{2}{3}}{15}$ $= 86\frac{1}{9}$
	$=$	$= \beta_{15,86\frac{1}{9}}$
D^{f_1}		$\beta_{e2e}^{l.o.f_1} = b^{f_1}$ $15 \cdot \left[t - 86\frac{1}{9} \right]^+ = 25$ $t = 87\frac{7}{9}$
B^{f_1}		$\alpha^{f_1} \left(T_{e2e}^{l.o.f_1} \right) = 5 \cdot 86\frac{1}{9} + 25$ $= 455\frac{5}{9}$