



## Node\_1Flow



- $\beta_{v_0} = \beta_{R_{v_0}, T_{v_0}} = \beta_{10,10}$
- $\alpha^{f_0} = \gamma_{r^{f_0}, b^{f_0}} = \gamma_{5,25}$

	TFA	FIFO_MUX	ARB_MUX
$v_0$	$\alpha_{v_0} = \alpha^{f_0}$	$= \gamma_{5,25}$	
	$D^{f_0}$	$\beta_{v_0} = b_{v_0}$ $10 \cdot [t - 10]^+ = 25$ $t = 12\frac{1}{2}$	FIFO per micro flow $\beta_{v_0} = b_{v_0}$ $10 \cdot [t - 10]^+ = 25$ $t = 12\frac{1}{2}$
	$B^{f_0}$	$\alpha_{v_0}(T_{v_0}) = 5 \cdot 10 + 25 = 75$	
SFA, PMOO			FIFO_MUX (SFA only)   ARB_MUX
$v_0$	$\alpha_{v_0}^{x f_0}$		$= \gamma_{0,0}$
	$\beta_{e_{2e}}^{l.o.f_0} = [\beta_{v_0} - \alpha_{v_0}^{x f_0}]^+ = \beta_{R_{e_{2e}}^{l.o.f_0}, T_{e_{2e}}^{l.o.f_0}} = \beta_{v_0}$		$= \beta_{10,10}$
	$D^{f_0}$	$\beta_{e_{2e}}^{l.o.f_0} = b^{f_0}$ $10 \cdot [t - 10]^+ = 25$ $t = 12\frac{1}{2}$	
$B^{f_0}$	$\alpha^{f_0}(T_{e_{2e}}^{l.o.f_0}) = 5 \cdot 10 + 25 = 75$		

## Node\_2Flows\_1AC



- $\beta_{v_0} = \beta_{R_{v_0}, T_{v_0}} = \beta_{10,10}$
- $\alpha^{f_0} = \alpha^{f_1} = \gamma_{r^{f_i}, b^{f_i}} = \gamma_{5,25}, i \in \{0,1\}$


**Flows**  $f_i, i \in \{0,1\}$

TFA results will be equal for all flows as they share the same path of servers.  
SFA and PMOO are equal in single hop networks.

	TFA	FIFO_MUX	ARB_MUX
$v_0$	$\alpha_{v_0} = \alpha^{f_0} + \alpha^{f_1}$	$= \gamma_{10,50}$	
	$D^{f_i}$	$\beta_{v_0} = b_{v_0}$ $10 \cdot [t - 10]^+ = 50$ $t = 15$	$\beta_{v_0} = \alpha_{v_0}$ $10 \cdot [t - 10]^+ = 10 \cdot t + 50$ $0 \cdot t = 150$ $\Rightarrow D^{f_i} = \infty$
	$B^{f_i}$	$\alpha_{v_0}(T_{v_0}) = 10 \cdot 10 + 50$ $= 150$	

SFA, PMOO		FIFO_MUX (SFA only)	ARB_MUX	
$v_0$	$\alpha_{v_0}^{x f_i} = \alpha^{f_i}$		$= \gamma_{5,25}$	
	$\beta_{v_0}^{l.o.f_i} = [\beta_{v_0} - \alpha_{v_0}^{x f_i}]^+ = \beta_{R_{v_0}^{l.o.f_i}, T_{v_0}^{l.o.f_i}}$	$R_{v_0}^{l.o.f_i}$	$[R_{v_0} - r_{v_0}^{x f_i}]^+ = 5$	
		$T_{v_0}^{l.o.f_i}$	$\beta_{v_0} = b_{v_0}^{x f_i}$ $10 \cdot [t - 10]^+ = 25$ $t = 12\frac{1}{2}$	$\beta_{v_0} = \alpha_{v_0}^{x f_i}$ $10 \cdot [t - 10]^+ = 5 \cdot t + 25$ $t = 25$
		=	$= \beta_{5,12\frac{1}{2}}$	$= \beta_{5,25}$
	$\beta_{e_{2e}}^{l.o.f_i} = \beta_{v_0}^{l.o.f_i}$		$= \beta_{5,12\frac{1}{2}}$	$= \beta_{5,25}$
$D^{f_i}$		$\beta_{e_{2e}}^{l.o.f_i} = b^{f_i}$ $5 \cdot [t - 12\frac{1}{2}]^+ = 25$ $t = 17\frac{1}{2}$	$\beta_{e_{2e}}^{l.o.f_i} = b^{f_i}$ $5 \cdot [t - 25]^+ = 25$ $t = 30$	
$B^{f_i}$		$\alpha^{f_i}(T_{e_{2e}}^{l.o.f_i}) = 5 \cdot 12\frac{1}{2} + 25$ $= 87\frac{1}{2}$	$\alpha^{f_i}(T_{e_{2e}}^{l.o.f_i}) = 5 \cdot 25 + 25$ $= 150$	

## Node\_2Flow\_2ACs



- $\beta_{v_0} = \beta_{R_{v_0}, T_{v_0}} = \beta_{10,10}$
- $\alpha^{f_0} = \gamma_{r^{f_0}, b^{f_0}} = \gamma_{4,10}$
- $\alpha^{f_1} = \gamma_{r^{f_1}, b^{f_1}} = \gamma_{5,25}$

**Flows**  $f_i, i \in \{0, 1\}$

TFA results will be equal for all flows as they share the same path of servers.

	TFA	FIFO_MUX	ARB_MUX
$v_0$	$\alpha_{v_0} = \alpha^{f_0} + \alpha^{f_1}$	$= \gamma_{9,35}$	
	$D^{f_i}$	$\beta_{v_0} = b_{v_0}$ $10 \cdot [t - 10]^+ = 35$ $t = 13\frac{1}{2}$	$\beta_{v_0} = \alpha_{v_0}$ $10 \cdot [t - 10]^+ = 9 \cdot t + 35$ $t = 135$
	$B^{f_i}$	$\alpha_{v_0}(T_{v_0}) = 9 \cdot 10 + 35 = 125$	

**Flow  $f_0$**

SFA and PMOO are equal in single hop networks.

SFA. PMOO		FIFO_MUX (SFA only)	ARB_MUX	
$v_0$	$\alpha_{v_0}^{xf_0} = \alpha^{f_1}$		$= \gamma_{5,25}$	
	$\beta_{v_0}^{l.o.f_0} = [\beta_{v_0} - \alpha_{v_0}^{xf_0}]^+ = \beta_{R_{v_0}^{l.o.f_0}, T_{v_0}^{l.o.f_0}}$	$R_{v_0}^{l.o.f_0}$	$[R_{v_0} - r_{v_0}^{xf_0}]^+ = 5$	
		$T_{v_0}^{l.o.f_0}$	$\beta_{v_0} = b_{v_0}^{xf_0}$ $10 \cdot [t - 10]^+ = 25$ $t = 12\frac{1}{2}$	$\beta_{v_0} = \alpha_{v_0}^{xf_0}$ $10 \cdot [t - 10]^+ = 5 \cdot t + 25$ $t = 25$
		=	$= \beta_{5,12\frac{1}{2}}$	$= \beta_{5,25}$
	$\beta_{e_{2e}}^{l.o.f_0} = \beta_{R_{e_{2e}}^{l.o.f_0}, T_{e_{2e}}^{l.o.f_0}} = \beta_{v_0}^{l.o.f_0}$		$= \beta_{5,12\frac{1}{2}}$	$= \beta_{5,25}$
$D^{f_0}$	$\beta_{e_{2e}}^{l.o.f_0} = b^{f_0}$ $5 \cdot [t - 12\frac{1}{2}]^+ = 10$ $t = 14\frac{1}{2}$	$\beta_{e_{2e}}^{l.o.f_0} = b^{f_0}$ $5 \cdot [t - 25]^+ = 10$ $t = 27$		
$B^{f_0}$	$\alpha^{f_0}(T_{e_{2e}}^{l.o.f_0}) = 4 \cdot 12\frac{1}{2} + 10$ $= 60$	$\alpha^{f_0}(T_{e_{2e}}^{l.o.f_0}) = 4 \cdot 25 + 10$ $= 110$		

**Flow  $f_1$**

SFA and PMOO are equal in single hop networks.

SFA, PMOO		FIFO_MUX (SFA only)	ARB_MUX	
$v_0$	$\alpha_{v_0}^{xf_1} = \alpha^{f_0}$		$= \gamma_{4,10}$	
	$\beta_{v_0}^{l.o.f_1} = [\beta_{v_0} - \alpha_{v_0}^{xf_1}]^+ = \beta_{R_{v_0}^{l.o.f_1}, T_{v_0}^{l.o.f_1}}$	$R_{v_0}^{l.o.f_1}$	$[R_{v_0} - r_{v_0}^{xf_1}]^+ = 6$	
		$T_{v_0}^{l.o.f_1}$	$\beta_{v_0} = b_{v_0}^{xf_1}$ $10 \cdot [t - 10]^+ = 10$ $t = 11$	$\beta_{v_0} = \alpha_{v_0}^{xf_1}$ $10 \cdot [t - 10]^+ = 4 \cdot t + 10$ $t = 18\frac{1}{3}$
		=	$= \beta_{6,11}$	$= \beta_{6,18\frac{1}{3}}$
	$\beta_{e_{2e}}^{l.o.f_1} = \beta_{R_{e_{2e}}^{l.o.f_1}, T_{e_{2e}}^{l.o.f_1}} = \beta_{v_0}^{l.o.f_1}$		$= \beta_{6,11}$	$= \beta_{6,18\frac{1}{3}}$
$D^{f_0}$	$\beta_{e_{2e}}^{l.o.f_1} = b^{f_1}$ $6 \cdot [t - 11]^+ = 25$ $t = 15\frac{1}{6}$	$\beta_{e_{2e}}^{l.o.f_1} = b^{f_1}$ $6 \cdot [t - 18\frac{1}{3}]^+ = 25$ $t = 22\frac{1}{2}$		
$B^{f_0}$	$\alpha^{f_1}(T_{e_{2e}}^{l.o.f_1}) = 5 \cdot 11 + 25$ $= 80$	$\alpha^{f_1}(T_{e_{2e}}^{l.o.f_1}) = 5 \cdot 18\frac{1}{3} + 25$ $= 116\frac{2}{3}$		

### Node\_10Flow\_10ACs

- $\beta_{v_0} = \beta_{R_{v_0}, T_{v_0}} = \beta_{10,10}$
- for  $i = 0$  to  $9$ :  $\alpha^{f_i} = \gamma_{r^{f_i}, b^{f_i}} = \gamma_{\frac{1}{10} \cdot (i+1), 1 \cdot (i+1)}$

**Flows**  $f_i, i \in \{0, \dots, 9\}$

TFA results will be equal for all flows as they share the same path of servers.

	TFA	FIFO_MUX	ARB_MUX
$v_0$	$\alpha_{v_0} = \sum_{i=0}^9 \alpha_i$	$= \gamma_{5\frac{1}{2}, 55}$	
	$D^{f_i}$	$\beta_{v_0} = b_{v_0}$ $10 \cdot [t - 10]^+ = 55$ $t = 15\frac{1}{2}$	$\beta_{v_0} = \alpha_{v_0}$ $10 \cdot [t - 10]^+ = 5\frac{1}{2} \cdot t + 55$ $t = 34\frac{4}{9}$
	$B^{f_i}$	$\alpha_{v_0}(T_{v_0}) = 5\frac{1}{2} \cdot 10 + 55$ $= 110$	

**Flow  $f_0$**

SFA and PMOO are equal in single hop networks.

SFA, PMOO		FIFO_MUX (SFA only)	ARB_MUX	
$v_0$	$\alpha_{v_0}^{xf_0} = \sum_{i=1}^9 \alpha^{f_i} = \gamma_{r_{v_0}^{xf_0}, b_{v_0}^{xf_0}}$	$r_{v_0}^{xf_0}$	$\sum_{i=1}^9 r^{f_i} = 5\frac{2}{5}$	
		$b_{v_0}^{xf_0}$	$\sum_{i=1}^9 b^{f_i} = 54$	
		=	$= \gamma_{5\frac{2}{5}, 54}$	
	$\beta_{v_0}^{l.o.f_0} = [R_{v_0} - \alpha_{v_0}^{xf_0}]^+ = \beta_{R_{v_0}^{l.o.f_0}, T_{v_0}^{l.o.f_0}}$	$R_{v_0}^{l.o.f_0}$	$[R_{v_0} - r_{v_0}^{xf_0}]^+ = 4\frac{3}{5}$	$\beta_{v_0} = \alpha_{v_0}^{xf_0}$
		$T_{v_0}^{l.o.f_0}$	$\beta_{v_0} = b_{v_0}^{xf_0}$ $10 \cdot [t - 10]^+ = 54$ $t = 15\frac{2}{5}$	$10 \cdot [t - 10]^+ = 5\frac{2}{5} \cdot t + 54$ $t = 33\frac{11}{23}$
		=	$= \beta_{4\frac{3}{5}, 15\frac{2}{5}}$	$= \beta_{4\frac{3}{5}, 33\frac{11}{23}}$
	$\beta_{e_{2e}}^{l.o.f_0} = \beta_{R_{e_{2e}}^{l.o.f_0}, T_{e_{2e}}^{l.o.f_0}} = \beta_{v_0}^{l.o.f_0}$		$= \beta_{4\frac{3}{5}, 15\frac{2}{5}}$	$= \beta_{4\frac{3}{5}, 33\frac{11}{23}}$
	$D^{f_0}$	$\beta_{e_{2e}}^{l.o.f_0} = b^{f_0}$	$\beta_{e_{2e}}^{l.o.f_0} = b^{f_0}$	$\beta_{e_{2e}}^{l.o.f_0} = b^{f_0}$
$4\frac{3}{5} \cdot [t - 15\frac{2}{5}]^+ = 1$ $t = 15\frac{71}{15}$		$4\frac{3}{5} \cdot [t - 33\frac{11}{23}]^+ = 1$ $t = 33\frac{16}{23}$	$4\frac{3}{5} \cdot [t - 33\frac{11}{23}]^+ = 1$ $t = 33\frac{16}{23}$	
$B^{f_0}$	$\alpha^{f_0}(T_{e_{2e}}^{l.o.f_0}) = \frac{1}{10} \cdot 15\frac{2}{5} + 1$	$\alpha^{f_0}(T_{e_{2e}}^{l.o.f_0}) = \frac{1}{10} \cdot 15\frac{2}{5} + 1$	$\alpha^{f_0}(T_{e_{2e}}^{l.o.f_0}) = \frac{1}{10} \cdot 33\frac{11}{23} + 1$	
	$= 2\frac{27}{50}$	$= 2\frac{27}{50}$	$= 4\frac{8}{23}$	

**Flow  $f_6$**

SFA and PMOO are equal in single hop networks.

SFA, PMOO		FIFO_MUX (SFA only)	ARB_MUX	
$v_0$	$\alpha^{xf_6} = \sum_{i=0}^5 \alpha^{f_i} + \sum_{i=7}^9 \alpha^{f_i} = \gamma_{r_{v_0}^{xf_6}, b_{v_0}^{xf_6}}$	$r_{v_0}^{xf_6}$	$(\sum_{i=0}^9 r^{f_i}) - r^{f_6} = 4\frac{4}{5}$	
		$b_{v_0}^{xf_6}$	$(\sum_{i=0}^9 b^{f_i}) - b^{f_6} = 48$	
		=	$= \gamma_{4\frac{4}{5}, 48}$	
	$\beta_{v_0}^{1.o.f_6} = [\beta_{v_0} - \alpha_{v_0}^{xf_6}]^+ = \beta_{R_{v_0}^{1.o.f_6}, T_{v_0}^{1.o.f_6}}$	$R_{v_0}^{1.o.f_6}$	$[R_{v_0} - r_{v_0}^{xf_6}]^+ = 5\frac{1}{5}$	
		$T_{v_0}^{1.o.f_6}$	$\beta_{v_0} = b_{v_0}^{xf_6}$ $10 \cdot [t - 10]^+ = 48$ $t = 14\frac{4}{5}$	$\beta_{v_0} = \alpha_{v_0}^{xf_6}$ $10 \cdot [t - 10]^+ = 4\frac{4}{5} \cdot t + 48$ $t = 28\frac{6}{13}$
		=	$= \beta_{5\frac{1}{5}, 14\frac{4}{5}}$	$= \beta_{5\frac{1}{5}, 28\frac{6}{13}}$
		$\beta_{e2e}^{1.o.f_6} = \beta_{R_{e2e}^{1.o.f_6}, T_{e2e}^{1.o.f_6}}$	$= \beta_{5\frac{1}{5}, 14\frac{4}{5}}$	$= \beta_{5\frac{1}{5}, 28\frac{6}{13}} = \beta_{v_0}^{1.o.f_6}$
	$D^{f_6}$	$\beta_{e2e}^{1.o.f_6} = b^{f_6}$	$\beta_{e2e}^{1.o.f_6} = b^{f_6}$	$\beta_{e2e}^{1.o.f_6} = b^{f_6}$
		$5\frac{1}{5} \cdot [t - 14\frac{4}{5}]^+ = 7$ $t = 16\frac{19}{130}$	$5\frac{1}{5} \cdot [t - 28\frac{6}{13}]^+ = 7$ $t = 29\frac{21}{26}$	
	$B^{f_6}$	$\alpha^{f_6}(T_{e2e}^{1.o.f_6}) = \frac{7}{10} \cdot 14\frac{4}{5} + 7$	$\alpha^{f_6}(T_{e2e}^{1.o.f_6}) = \frac{7}{10} \cdot 28\frac{6}{13} + 7$	
$= 17\frac{9}{25}$		$= 26\frac{12}{13}$		